

THE MODEL MATCHING PROBLEM FOR A GENERAL CLASS OF NON-LINEAR DISCRETE INPUT - OUTPUT SYSTEMS WITH CROSS-PRODUCTS. AN ALGORITHMIC APPROACH.

*Stelios Kotsios,
University of Athens, Department of Economics,
Division of Mathematics and Computer Science
Pesmazoglou 8, 10559 Athens, Greece*

Abstract: In this paper we examine the model matching problem that concerns nonlinear input - output discrete systems, containing products among delays of input and output signals, through a special factorization. The algebraic framework of $\delta\epsilon$ -operators and the star-product that we adopt describe these systems. Moreover, a certain procedure that resembles the Euclidean division, allows us to discover the linear factors of those systems, with respect to the above mentioned operations. The entire approach is symbolically algorithmic and involves the use of suitable software.

Keywords: Nonlinear, Discrete, Algebraic Geometry, Model Matching, Algorithmic, Computational, Cross-products.

1 Introduction

As is well known, nonlinear systems are used in a variety of applications and have been the focus of research for a number of years. This, along with a recent increase in their use, has led to a steady development of the relevant theory. Furthermore, various advances in computer technology have had a major effect on control system analysis and design. These advances have led to the development of new algorithms and techniques, which in turn have allowed design methods to be accomplished with greater speed and efficiency, [13]. Yet, computational methods for the study of nonlinear systems are (still) at an early stage of development. Such computational methods have been applied in the study of modeling, the problem of feedback linearization, and in the global optimization problem, ([3],[4],[13], to mention but a few). All of these problems were investigated mostly in relation to continuous systems, and, in some cases, in relation to non-linear discrete time systems, [14]. By definition, a discrete time system evaluates input and output signals over a countable number of time instants. In some cases, a discrete time system is obtained from continuous time systems through sampling at certain time instants [17]. A further case concerns systems that are naturally and directly described in discrete form, typically in financial or economic systems. There is a rich literature devoted to the study of discrete systems. Certain works approach the issue through analytical tools, as the Lie Derivatives and Distributions [6],[8] and others by using algebraic methodologies, like differential algebra or rings theory, [3],[4],[5],[7],[27]. Some researchers give algorithmic results [5] and others study the discrete systems from the theoretical point of view [23],[24]. An important feature of discrete systems is their strong computational orientation. This is connected to the fact that the procedures developed for these systems are more "suitable" for realization in computational machines. Thus, several design techniques can be accomplished at a faster rate and in a way that makes them appropriate for further applications.

The present paper focuses on nonlinear discrete input-output systems of the form:

$$\begin{aligned}
& y(t) + \sum a_i y(t-i) + \sum \sum a_{i_1 i_2} y(t-i_1) y(t-i_2) + \cdots + \\
& + \sum \sum \cdots \sum a_{i_1 i_2 \dots i_n} y(t-i_1) \cdots y(t-i_n) = \\
& = \sum b_j u(t-j) + \cdots + \sum \sum \cdots \sum b_{j_1 j_2 \dots j_m} u(t-j_1) \cdots u(t-j_m) + \\
& + \sum \sum c_{kl} y(t-k) u(t-l) + \cdots + \sum \sum \sum \cdots \sum \sum \cdots \sum \\
& c_{k_1 k_2 \dots k_{n'} l_1 l_2 \dots l_v} y(t-k_1) \cdots y(t-k_{n'}) u(t-l_1) \cdots u(t-l_v)
\end{aligned} \tag{1}$$

Equation (1) transforms causal input signals (i.e. $u(t) = 0$ for $t < 0$) to causal output signals. A set of initial conditions $y(0) = y_0, y(1) = y_1, \dots, y(k) = y_k$ is always assigned to (1) and the lowest delay output term (that is $y(t)$) appears in the linear part of the system. From all the above, we conclude that for any given input sequence the entire future output is uniquely determined, [16]. The systems of the form (1), which contain products among inputs and output signals, that are sometimes called 'cross-products', encompass a broad variety of nonlinear discrete systems. We obtain these either through transformations of nonlinear discrete state-space representations into input - output forms [20], or when we use Taylor's expansion method to approximate other more general nonlinear discrete systems [16], [20]. These are employed in signal processing theory, whenever it is necessary to construct nonlinear representations of discrete signals, (they are an extension of the infinite impulse response filters to a nonlinear set up, [16]), in nonlinear time-series analysis and in adaptive control, in the context of designing nonlinear adaptive controllers, [26]. Design problems for such systems have been studied in the past through the use of either analytical or algebraic tools (see for instance [3], [5], [19]). We have to mention here especially the following works [23], [24] which study the above systems by means of algebraic methods and provide us with theoretical results.

In this paper we would like to propose a novel way of dealing with systems of the form (1) within a computer algebra environment. We do this initially by means of special operators and operations that create an appropriate algebraic framework and then through the development of symbolic computational algorithms that allow us to solve the model matching's design problem. Specifically, we use the so-called $\delta\epsilon$ -operator to deal with cross-products. This operator, introduced in [10], is an extension of the simple δ and ϵ -operators that are used in the algebraic description of nonlinear discrete input - output systems without cross-products [11], and which are also an extension of the simple shift operator q in linear discrete systems [21]. Via these operators we can define the so-called δ, ϵ and $\delta\epsilon$ - polynomials. These polynomials involve the delays of output and input signals in a nonlinear polynomial way, and are similar to polynomials with many variables. (A special case of them are the linear polynomials). By means of these polynomials we can formally rewrite (1) as follows: $F[y(t), u(t)] = 0$, where F a $\delta\epsilon$ -polynomial. Among these polynomials, we can define two product operations: the dot-product, which corresponds to the usual product among polynomials, and the star-product, which corresponds to the substitution of one polynomial by another, or, in more system-oriented terminology, to the cascade connection of systems. Though there is a similarity between this algebraic background and others, there is also the interesting peculiarity that the set of $\delta\epsilon$ -polynomials with respect to the star-product is not a ring, [3]. Indeed, the property $A * (B + C) = A * B + A * C$ is NOT

The concept of formal δ or ϵ -linear factors is presented here and departs from previous approaches, [9]. The basic idea underlying this concept, is that it “reveals”, through appropriate algorithms, the linear δ or ϵ -polynomials that are hidden within a nonlinear $\delta\epsilon$ -polynomial F and they are factors of F with respect either to the dot-product or to the star-product. Specifically, if F is a given $\delta\epsilon$ -polynomial, then we can rewrite it as:

$$F = \sum_{\theta} \delta_0^{\kappa_{\theta}} \epsilon_0^{\sigma_{\theta}} \cdot (c_{\theta} \delta_{i_{\theta}} \epsilon_{j_{\theta}} * [L_{\theta}, M_{\theta}]) + \mathbf{R}_{\delta,h} + \mathbf{R}_{\epsilon,h} + \mathbf{R}_{\delta\epsilon} \quad (2)$$

where, in general, the coefficients c_{θ} , the linear polynomials L_{θ}, M_{θ} and the remainders $\mathbf{R}_{\delta,h}, \mathbf{R}_{\epsilon,h}, \mathbf{R}_{\delta\epsilon}$, depend on the parameters w_{ijhk}, s_{ijhk} . These polynomials L_{θ}, M_{θ} are the linear formal factors of F , upon discussion. The immediate consequence of this factorization is that we can transfer questions about the behaviour of the nonlinear system to questions about the structure of the linear polynomials it “contains” and apply well-known methods for dealing with those polynomials. The above expression of a given $\delta\epsilon$ -polynomial, is achieved by means of certain computational algorithms. These algorithms are simply a kind of division among $\delta\epsilon$ -polynomials with respect to the star-product. Though this procedure resembles the method of Gröbner basis [2], there are some essential differences: (1) The set of $\delta\epsilon$ -polynomials is not a ring. (2) Here we are using just one $\delta\epsilon$ -polynomial, instead of a set of such polynomials. (3) It involves the notion of free parameters. We can then achieve certain tasks by giving suitable values to those parameters. For instance, we can eliminate the remainders $\mathbf{R}_{\delta,h}, \mathbf{R}_{\epsilon,h}, \mathbf{R}_{\delta\epsilon}$ or we can find the common factors of the polynomials L_{θ}, M_{θ} , if any. All these can be implemented in a computer and an appropriate software has already been created through the Mathematica Package, which was used throughout this paper. To elucidate the whole issue, let us present a short exhibitory example. Let us have the bilinear system: $y(t) + y(t-1) = u(t-1) + y(t-2)u(t-1)$. This system can be rewritten as $(\delta_0 + \delta_1 - \epsilon_1 - \delta_2\epsilon_1)[y(t), u(t)] = 0$ or $F[y(t), u(t)] = 0$, where F is the δ -polynomial $\delta_0 + \delta_1 - \epsilon_1 - \delta_2\epsilon_1$. F can be written as:

$$\begin{aligned} & \delta_0 + \delta_1 - \epsilon_1 - \delta_0\epsilon_0 * [w_{1,0,0,0}\delta_0 + w_{1,0,0,1}\delta_1 + \delta_2, s_{1,0,0,0}\epsilon_0 + \epsilon_1] + s_{1,0,0,0}\delta_0\epsilon_0 * [w_{2,0,0,0}\delta_0 + \\ & + w_{2,0,0,1}\delta_1 + \delta_2, \epsilon_0] + w_{1,0,0,1}\delta_0\epsilon_0 * [w_{3,0,0,0}\delta_0 + \delta_1, s_{3,0,0,0}\epsilon_0 + \epsilon_1] + (w_{1,0,0,1}s_{1,0,0,0} - \\ & - w_{2,0,0,1}s_{1,0,0,0} - w_{1,0,0,1}s_{3,0,0,0})\delta_0\epsilon_0 * [w_{4,0,0,0}\delta_0 + \delta_1, \epsilon_0] + \\ & + (w_{1,0,0,0} - w_{1,0,0,1}w_{3,0,0,0})\delta_0\epsilon_0 * [\delta_0, s_{5,0,0,0}\epsilon_0 + \epsilon_1] + \mathbf{R}_{\delta\epsilon} \end{aligned}$$

(we do not write $\mathbf{R}_{\delta\epsilon}$ explicitly, due to its large size). The exact meaning of the indexes in the above expression will be explained later. The set of the Formal Linear factors of F is: $\{\delta_0 + \delta_1, \epsilon_1, w_{1,0,0,0}\delta_0 + w_{1,0,0,1}\delta_1 + \delta_2, s_{1,0,0,0}\epsilon_0 + \epsilon_1, w_{2,0,0,0}\delta_0 + w_{2,0,0,1}\delta_1 + \delta_2, \epsilon_0, w_{3,0,0,0}\delta_0 + \delta_1, s_{3,0,0,0}\epsilon_0 + \epsilon_1, w_{4,0,0,0}\delta_0 + \delta_1, \delta_0, s_{5,0,0,0}\epsilon_0 + \epsilon_1\}$. By giving to the parameters $w_{i,0,0,j}, s_{i,0,0,j}$ certain values we can take concrete expressions for the system. For instance, if we put $w_{1,0,0,0} = 16, w_{1,0,0,1} = -10, w_{2,0,0,0} = 1, w_{2,0,0,1} = 1, w_{3,0,0,0} = -1, w_{4,0,0,0} = -\frac{33}{26}, s_{1,0,0,0} = 2, s_{3,0,0,0} = -3, s_{6,0,0,0} = -1$ we can eliminate the remainder $\mathbf{R}_{\delta\epsilon}$ and F takes the form: $F = \delta_0 + \delta_1 - \epsilon_1 - \delta_0\epsilon_0 * [16\delta_0 - 10\delta_1 + \delta_2, 2\epsilon_0 + \epsilon_1] + 2\delta_0\epsilon_0 * [\delta_0 + \delta_1 + \delta_2, \epsilon_0] - 10\delta_0\epsilon_0 * [-\delta_0 + \delta_1, -3\epsilon_0 + \epsilon_1] + 52\delta_0\epsilon_0 * [-\frac{33}{26}\delta_0 + \delta_1, \epsilon_0] + 6\delta_0\epsilon_0 * [\delta_0, -\epsilon_0 + \epsilon_1]$.

As a main application of the above methodology, we examine the model-matching problem for those systems. This specific problem concerns the discovery of linear feedback connec-

choice of such a desired system can turn the problem into one that concerns tracking. In order to clarify our way of facing up the problem, let us recall some well known ideas from the theory of linear systems. Let us have the linear input - output system:

$$a_0y(t) + a_1y(t-1) + \dots + a_ky(t-k) = b_1u(t-1) + b_2u(t-2) + \dots + b_mu(t-m)$$

we want to find a feedback connection so that the closed-loop system behaves like a given desired linear system. By means of the operator q , where $q^{-1}y(t) = y(t-1)$, we rewrite the original system and the desired system algebraically as: $Ay(t) = Bu(t)$, $A_d y^*(t) = B_d u_c(t)$, where A, B, A_d, B_d , proper polynomials of the single variable q^{-1} . We define the feedback-law upon request to be of the form $Ru = Tu_c - Sy$, where R, T, S polynomials of q^{-1} to be determined. Using the fact that in the linear case, the usual product among polynomials corresponds to the cascade connection of systems (i.e. if $y(t) = Gu(t)$ and $u(t) = Fv(t)$ then $y(t) = GFv(t)$) we take the closed-loop system $(RA + BS)y(t) = BTu_c(t)$. Assuming that $y = y^*$ we obtain the polynomials R, S, T by solving the equations $RA + BS = A_d$, $BT = B_d$, [21].

The question, which naturally arises, is how can we extend the above approach in the case of nonlinear discrete input-output system. We firstly faced this problem in the paper [11], where we introduced the δ -operator in order to replace the q operator and the star-product instead of the common product, (therefore the star-product corresponds to the cascade connection of nonlinear input-output systems). By means of those tools we managed to solve the problem only for input-output systems with nonlinear output, linear input and without cross-products between input and output signals. Extension of those results can be found at [12],[14],[15],[25]. The aim of the current paper is to present a solution of the model matching problem for a general class of nonlinear input-output systems with nonlinearities in the output, in the input, and with cross-products. Essentially, what we are doing here is to reduce the feedback designing questions to the linear factors L_θ, M_θ , appeared at the original system. Indeed, if a feedback-law $u(t) = Sy(t)$ is available, then the system (1) is transformed to a closed-loop form which is nothing else than a difference equation with respect to $y(t)$. the core of our approach is to find conditions which guarantee that all the terms of the said difference equation have a common linear factor. To achieve that we use $\delta\epsilon$ -operators and some suitable algorithms to express (1) as (2). Then, we throw away the remainders $R_{\delta\epsilon}, R_{\epsilon,h}, R_{\delta,h}$ and we seek for those values of the free parameters and the quantity S , which provide us with linear polynomials L_θ, M_θ , which are not prime among each other. Let us denote their common factor by Φ . If the desired system coincides with Φ or it has common factor with it, then the previous feedback-law solves the problem for proper initial conditions. Our emphasis is on the fact that the original nonlinear design has been reduced to numerous operations among linear polynomials, which can be carried out by means of well known techniques of algebraic geometry.

Moreover, our approach in the present paper will be purely formal and we will not address any issues that pertain to internal stability. We take the main advantages of our approach to be the following: (a) that it is a symbolic algorithmic orientation that allows a direct computer implementation. (b) that it allows the emergence of a set of solutions for each of the model matching problem above, as opposed to a single solution. This is of vital importance, since it allows us to choose between available solutions in a way that is informed by further constraints. There is strong evidence that this approach, if successful, may

or optimal controllers design theory. A consideration of these problems, along with an assessment of the success of current methods on the basis of specific examples, will be the subject matter of a future paper.

The present paper is divided into two parts. In Part I we present the algebraic framework and the algorithms, in Part II we are dealing with the model-matching problem. Throughout the paper, $\mathbf{N}, \mathbf{Z}, \mathbf{Z}^+, \mathbf{R}$ will denote the sets of natural, integers, positive integers, rational and real numbers, respectively.

2 The δ -operators and δ -polynomials

In this section we recall the notions of δ -operators and δ -polynomials. They have been appeared and studied in [11], [12], [18]. The scope of their presentation here is to constitute an introductory framework for the consideration of the $\delta\epsilon$ -operators and $\delta\epsilon$ -polynomials, which are going to be adopted at the next section. Let $y(t)$ be a real causal sequence, that is a function $y : \mathbf{Z} \rightarrow \mathbf{R}$ with the property $y(t) = 0$, for $t < 0$. We denote the set of such sequences by F . It is originating from the sampling of continuous functions. Let $\mathbf{i}$ be an ordered element of the set $\mathbf{Z}^{+n}$, in other words, $\mathbf{i} = (i_1, i_2, \dots, i_n)$ is a vector with n positive integers as components, placed in an ascending way ($i_1 \leq i_2 \leq \dots \leq i_n$). We call $\mathbf{i}$ a multi-index with dimension n . The δ -operator $\delta_{\mathbf{i}} : F \rightarrow F$ is defined as follows:

$$\delta_{\mathbf{i}}y(t) = \delta_{i_1}\delta_{i_2} \cdots \delta_{i_n}y(t) = y(t - i_1)y(t - i_2) \cdots y(t - i_n)$$

If in the multi-index $\mathbf{i}$ certain components are equal among each other, then we can use an alternate notation. Indeed, let $i_1 = i_2 = \dots = i_a = j$, $i_{a+1} = i_{a+2} = \dots = i_{a+b} = k$, $\dots, i_{n-c} = i_{n-c+1} = \dots = i_n = l$, then the operator $\delta_{\mathbf{i}}$ can be rewritten as $\delta_{\mathbf{i}} = \delta_j^a \delta_k^b \cdots \delta_l^c$. The quantity $a + b + \dots + c$ is called degree of $\delta_{\mathbf{i}}$ and it is denoted by $\deg(\delta_{\mathbf{i}})$. If $\mathbf{i}$ consists from one element $\mathbf{i} = (i)$, then we have the simple i -shift operator, i.e. $\delta_i y(t) = y(t - i)$. If at least one of the components of a multi-index is equal to zero then the operator is called *zero* operator. A special case of zero operator is the identical operator δ_0 , where $\delta_0 y(t) = y(t)$. By convention we define the *null* operator, δ_e as $\delta_e y(t) = 1$. In other words the symbol e corresponds to the " empty " multi-index $()$. The set of all δ -operators is denoted by Δ .

Example 2.1 *If $\mathbf{i} = (3)$, then $\delta_{\mathbf{i}}y(t) = \delta_3y(t) = \delta_3y(t) = y(t-3)$. If $\mathbf{i} = (1, 1, 1, 2, 3, 3, 4, 4)$, then $\delta_{\mathbf{i}}y(t) = \delta_{(1,1,1,2,3,3,4,4)}y(t) = \delta_1^3\delta_2\delta_3^2\delta_4^2y(t) = y^3(t-1)y(t-2)y^2(t-3)y^2(t-4)$. The operators $\delta_0y(t) = y(t)$, $\delta_0^2\delta_2^3y(t) = \delta_{(0,0,2,2,2)}y(t) = y^2(t)y^3(t-2)$ are both zero operators.*

Let $\mathbf{I}$ be set of multi-indexes. It may be ordered in a lexicographical way as follows: We say that the multi-index $\mathbf{i} = (i_1, i_2, \dots, i_n)$ is " less " than the multi-index $\mathbf{j} = (j_1, j_2, \dots, j_m)$, and we write $\mathbf{i} \prec \mathbf{j}$ if either $n < m$ or $n = m$ and the right-most nonzero entry of the vector $\mathbf{j} - \mathbf{i}$ is positive. For instance, $(10) \prec (9, 9) \prec (1, 1, 3, 3) \prec (1, 2, 3, 3)$. The order among multi-indexes implies an order among δ -operators in a natural way. Indeed, we say that $\delta_{\mathbf{i}} \prec \delta_{\mathbf{i}'}$ if $\mathbf{i} \prec \mathbf{i}'$. Therefore, $\delta_{10} \prec \delta_9^2 \prec \delta_1^2\delta_3^2 \prec \delta_1\delta_2\delta_3^2$. We equip the set of the δ -operators Δ , with two internal operations: the dot-product and the star-product. The dot-product corresponds to the usual product among sequences, while the star-product corresponds to the substitution of one sequence by another. Specifically, let

$z(t) = \delta_{\mathbf{i}}y(t) = y(t - i_1)y(t - i_2) \cdots y(t - i_n)$, $w(t) = \delta_{\mathbf{j}}y(t) = y(t - j_1)y(t - j_2) \cdots y(t - j_m)$. We define as dot-product of the operators $\delta_{\mathbf{i}}$ and $\delta_{\mathbf{j}}$ a new operator, denoted by $\delta_{\mathbf{i}} \cdot \delta_{\mathbf{j}}$, with the property: $\delta_{\mathbf{i}} \cdot \delta_{\mathbf{j}}y(t) = z(t)w(t) = y(t - i_1)y(t - i_2) \cdots y(t - i_n)y(t - j_1)y(t - j_2) \cdots y(t - j_m)$. Their star-product is a new operator, denoted by $\delta_{\mathbf{i}} * \delta_{\mathbf{j}}$, with the property: $\delta_{\mathbf{i}} * \delta_{\mathbf{j}}y(t) = \delta_{\mathbf{i}}w(t) = w(t - i_1)w(t - i_2) \cdots w(t - i_n) = y(t - j_1 - i_1)y(t - j_2 - i_1) \cdots y(t - j_m - i_1) \cdots y(t - j_1 - i_n)y(t - j_2 - i_n) \cdots y(t - j_m - i_n)$. In order to give compact formulas for the star and dot-products, we need the following operators among their multi-indexes. Given two multi-indexes $\mathbf{i} = (i_1, i_2, \dots, i_k)$ and $\mathbf{j} = (j_1, j_2, \dots, j_\lambda)$, the new multi-index $\mathbf{i} \oplus \mathbf{j}$ is defined just juxtaposing $\mathbf{j}$ after $\mathbf{i}$. Explicitly: $\mathbf{i} \oplus \mathbf{j} = (i_1, j_1, i_2, i_3, j_2, \dots, i_k, j_\lambda)$ where $i_1 \leq j_1 \leq i_2 \leq i_3 \leq j_2 \leq \dots \leq i_k \leq j_\lambda$. We define the pointwise sum $\mathbf{j} + i$ as follows: Let $\mathbf{j} = (j_1, j_2, \dots, j_m)$ be a multi-index and i an integer, then $\mathbf{j} + i = (j_1 + i, j_2 + i, \dots, j_m + i)$. Using those notations we get the following formulae:

Proposition 2.1 *The following properties are valid: (1) $\delta_{\mathbf{i}} \cdot \delta_{\mathbf{j}} = \delta_{\mathbf{i} \oplus \mathbf{j}}$, (2) $\delta_{\mathbf{i}} * \delta_{\mathbf{j}} = \delta_{\mathbf{j} + i_1} \cdot \delta_{\mathbf{j} + i_2} \cdots \delta_{\mathbf{j} + i_n}$*

Further properties, concerning the dot and the star products, can be found in [14],[18]. We can also define an external operation, named addition, as follows: $(\delta_{\mathbf{i}} + \delta_{\mathbf{j}})y(t) = \delta_{\mathbf{i}}y(t) + \delta_{\mathbf{j}}y(t)$. It can be easily proved that $\delta_{\mathbf{k}} * (\delta_{\mathbf{i}} + \delta_{\mathbf{j}}) \neq (\delta_{\mathbf{k}} * \delta_{\mathbf{i}}) + (\delta_{\mathbf{k}} * \delta_{\mathbf{j}})$ and thus the set $(\Delta, +, *)$ is not a ring.

Expressions of the form $A = \sum_{n=0}^w \sum_{\mathbf{i} \in \mathbf{I}_n} a_{\mathbf{i}} \delta_{\mathbf{i}}$ are called δ -polynomials, where by $\mathbf{I}_n$ we denote the set of multi-indexes with dimension n . By convention $\mathbf{I}_0 = \{\delta_e\}$. For each polynomial A we define $d(A)$ as follows: $d(A) = \min\{\min(i_1, i_2, \dots, i_n), \mathbf{i} = (i_1, i_2, \dots, i_n) \in \mathbf{Z}^{+n} \text{ such that } a_{\mathbf{i}} \neq 0, \text{ for } n = 1, 2, \dots, k\}$. We define as degree of A and we denote it by $\deg(A)$ the maximum $\deg(\delta)$ appeared in A . The maximum term of a non-linear polynomial A , denoted by $\max(A)$, is its largest term, accordingly to the lexicographical order defined in the previous section. An expression of the form $\sum_{\mathbf{i} \in \mathbf{Z}} a_{\mathbf{i}} \delta_{\mathbf{i}}$ is called a linear polynomial. Two δ -polynomials $A = \sum_{n=0}^{\nu} \sum_{\mathbf{i} \in \mathbf{I}_n} a_{\mathbf{i}} \delta_{\mathbf{i}}$ and $B = \sum_{m=0}^{\mu} \sum_{\mathbf{j} \in \mathbf{J}_m} b_{\mathbf{j}} \delta_{\mathbf{j}}$ are equal if $\nu = \mu$, $\mathbf{I}_n = \mathbf{J}_m$, $n = 0, 1, \dots, \nu$ and $a_{\mathbf{i}} = b_{\mathbf{j}}$. Their dot-product is defined as follows: $A \cdot B = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} \sum_{\mathbf{i} \in \mathbf{I}_n} \sum_{\mathbf{j} \in \mathbf{J}_m} a_{\mathbf{i}} b_{\mathbf{j}} \delta_{\mathbf{i}} \cdot \delta_{\mathbf{j}}$. This dot-product is nothing else than the classical product among polynomials with many variables. In order to define their star-product, we proceed as follows: Let us consider the δ -polynomials A and B as functions, transforming sequences to sequences, accordingly to the rules: $A : F \rightarrow F, w(t) \rightarrow Aw(t)$, $B : F \rightarrow F, y(t) \rightarrow By(t)$, then, the star-product $A * B$ is defined as:

$$A * B : F \rightarrow F \quad , \quad y(t) \rightarrow A * By(t) = A \circ By(t) = A(By(t))$$

There are certain formulae for the calculation of the star-product. A first one appeared in [11], another one is provided in [18]. For the sake of completeness of our presentation we shall present the first one, which is the more frequently used.

Proposition 2.2 *Let us suppose that we have the δ -polynomials $A = \sum_{n=0}^{\nu} \sum_{\mathbf{i}=(i_1, i_2, \dots, i_n) \in \mathbf{I}_n} a_{\mathbf{i}} \delta_{\mathbf{i}}$, $B = \sum_{m=0}^{\mu} \sum_{\mathbf{j} \in \mathbf{J}_m} b_{\mathbf{j}} \delta_{\mathbf{j}}$, their star-product is given by the relation:*

$$A * B = \sum_{n=0}^{\nu} \sum_{\mathbf{i}=(i_1, i_2, \dots, i_n) \in \mathbf{I}_n} \sum_{(\mathbf{j}_1, \mathbf{j}_2, \dots, \mathbf{j}_n) \in (\cup_m \mathbf{J}_m)^n} a_{\mathbf{i}} b_{\mathbf{j}_1} b_{\mathbf{j}_2} \cdots b_{\mathbf{j}_n} \delta_{\mathbf{j}_1 + i_1} \delta_{\mathbf{j}_2 + i_2} \cdots \delta_{\mathbf{j}_n + i_n}$$

Proposition 2.3 (1) $\delta_i * A = \sum_{n=0}^{\nu} \sum_{\mathbf{i} \in \mathbf{I}_n} a_{\mathbf{i}} \delta_{\mathbf{i}+i}$, $i \in \mathbf{Z}$ (2) $\delta_{\mathbf{i}} * A = (\delta_{i_1} * A) \cdot (\delta_{i_2} * A) \cdots (\delta_{i_n} * A)$, $\mathbf{i} = i_1, i_2, \dots, i_n$ (3) $\delta_{\mathbf{i}} * (A \cdot B) = (\delta_{\mathbf{i}} * A) \cdot (\delta_{\mathbf{i}} * B)$

The following propositions, can be found in [14].

Proposition 2.4 (1) $[A + B] * C = A * C + B * C$, (2) $C * [A + B] = C * A + C * B$ iff C linear, (3) $A * B \neq B * A$, (4) $(A * B) * \Gamma = A * (B * \Gamma)$, (5) $d(A * B) = d(A) + d(B)$, (6) $\deg(A * B) = \deg(A) \cdot \deg(B)$ (7) $(A \cdot B) * C = (A * C) \cdot (B * C)$.

The following property is very useful. It claims that working with linear δ -polynomials and the star-product it is like working with polynomials of a single variable and the classical product among them.

Proposition 2.5 Let $\mathbf{L}$ be the set of linear δ -polynomials, then the set $(\mathbf{L}, *, +)$ is a commutative ring and it is isomorphic to the ring $(R[x], \cdot, +)$, where $R[x]$ is the set of real polynomials of a single variable and $\cdot$ the operation of the polynomial product.

Proof: That $(\mathbf{L}, *, +)$ is a ring comes as a straightforward result of the proposition 2.4. For any linear δ -polynomial $M = \sum_{i=0}^k m_i \delta_i$ we define the map

$$\varphi : (\mathbf{L}, *, +) \rightarrow (R[x], \cdot, +) \quad , \quad \varphi(M) = \sum_{i=0}^k m_i x^i$$

It can be easily proved that $\varphi(M + N) = \varphi(M) + \varphi(N)$, N another linear δ -polynomial and that φ is one-to-one and onto. Let now $N = \sum_{j=0}^h n_j \delta_j$, then $M * N = \sum_{i=0}^k \sum_{j=0}^h m_i n_j \delta_{i+j}$. This means that $\varphi(M * N) = \sum_{i=0}^k \sum_{j=0}^h m_i n_j x^{i+j} = \sum_{\theta=0}^{k+h} (\sum_{s=0}^{\theta} m_s n_{\theta-s}) x^{\theta} = (\sum_{i=0}^k m_i x^i) \cdot (\sum_{j=0}^h n_j x^j) = \varphi(M) \cdot \varphi(N)$. This relation ensures that ϕ is an isomorphism and the theorem has been proved.

3 The $\delta\epsilon$ -operators and the $\delta\epsilon$ -polynomials

The δ -operators defined above, act on single sequences. This concept can help us to describe the delays appeared either in the input or in the output signal only. Nevertheless, a problem arises when we have to deal with cross-products. Specifically, let us suppose for instance, that we have the product $y^2(t-1)u^3(t-2)$, then using δ -operators we get $\delta_1^2 y(t) \delta_2^3 u(t)$. Hereafter, it is not clear how we shall handle this expression. The main difficulty is that we do not know which operator acts where. To pass over this obstacle we have to modify the notions of δ -operators and δ -polynomials in a proper way. Actually, we introduce the $\delta\epsilon$ -operator which acts instead of to a single sequence to a pair of sequences. This initially appeared in [10] and has been examined in [18]. Let $y(t), u(t)$ be two causal, real sequences, defined over the set of positive integers. Let i, j be integers. We define the $\delta_i \times \delta_j$ -operator as an operator acting on the pair $[y(t), u(t)]$ (actually, we had to denote this pair by $(y(t), u(t))$, but we use brackets in order to avoid so many parenthesis), as follows:

$$\delta_i \times \delta_j : F \times F \rightarrow F : \delta_i \times \delta_j [y(t), u(t)] = y(t-i)u(t-j)$$

Let $\mathbf{i} = (i_1, i_2, \dots, i_m), \mathbf{j} = (j_1, j_2, \dots, j_n)$ be multi-indexes. The operator $\delta_{\mathbf{i}} \times \delta_{\mathbf{j}} : F \times F \mapsto F$ is defined as:

This means that the operator $\delta_{\mathbf{i}}$ acts exclusively on " outputs " and $\delta_{\mathbf{j}}$ exclusively on " inputs ". Sometimes, for the sake of appearance, the following notation may be more convenient: $\delta_{\mathbf{i}} \times \delta_{\mathbf{j}} = \delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$. Therefore, the ϵ -operator is just an operator with poperties identical similar to the properties of δ -operator, except that it acts only on the second sequence (input). We call these operators $\delta\epsilon$ -operators and we denote their set by $\mathcal{D}$. Obviously, $\delta_{\mathbf{i}} \times \delta_e[y(t), u(t)] = \delta_{\mathbf{i}}y(t)$, $\delta_e \times \delta_{\mathbf{j}}(y, u) = \epsilon_{\mathbf{j}}u(t)$. A $\delta\epsilon$ -operator, $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$ with the property that $i_1 = j_1 = 0$, (in other words, the lowest delays of the δ and ϵ -parts of $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$ are zero), is called a *zero* $\delta\epsilon$ -operator. A special case of a zero $\delta\epsilon$ -operator is the operator $\delta_0\epsilon_0$, with $\delta_0\epsilon_0[y(t), u(t)] = y(t)u(t)$.

Example 3.1 Let $\mathbf{i} = (0, 1, 1, 2)$, $\mathbf{j} = (1, 1, 3, 3, 3)$, $\mathbf{r} = (0, 0, 1, 2)$ and $\mathbf{s} = (0, 1, 1, 2)$, then $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}}[y(t), u(t)] = \delta_{(0,1,1,2)} \epsilon_{(1,1,3,3,3)}[y(t), u(t)] = \delta_0\delta_1\delta_1\delta_2 \epsilon_1\epsilon_1\epsilon_3\epsilon_3\epsilon_3[y(t), u(t)] = \delta_0\delta_1^2\delta_2 \epsilon_1^2\epsilon_3^3[y(t), u(t)] = y(t)y^2(t-1)y(t-2)u^2(t-1)u^3(t-3)$, furthermore $\delta_{\mathbf{r}\epsilon_e}[y(t), u(t)] = \delta_{\mathbf{r}}y(t) = \delta_0^2\delta_1\delta_2y(t) = y^2(t)y(t-1)y(t-2)$ and $\delta_e\epsilon_{\mathbf{s}}[y(t), u(t)] = \epsilon_{\mathbf{s}}u(t) = \epsilon_0\epsilon_1^2\epsilon_2u(t) = u(t)u^2(t-1)u(t-2)$

The order among multi-indexes implies an order among $\delta\epsilon$ -operators in a natural way. Indeed, we say that $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}} \preceq \delta_{\mathbf{i}'\epsilon_{\mathbf{j}'}}$ if either $\mathbf{i} < \mathbf{i}'$ or $\mathbf{i} = \mathbf{i}'$ and $\mathbf{j} < \mathbf{j}'$. We equip the set of the $\delta\epsilon$ -operators with two internal operations: the dot-product and the star-product. Let $\delta_{\mathbf{i}} \times \delta_{\mathbf{j}} = \delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$, $\delta_{\mathbf{i}'} \times \delta_{\mathbf{j}'} = \delta_{\mathbf{i}'\epsilon_{\mathbf{j}'}}$ be two $\delta\epsilon$ -operators. As their dot-product, denoted by $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}} \cdot \delta_{\mathbf{i}'\epsilon_{\mathbf{j}'}}$, we define the operator:

$$(\delta_{\mathbf{i}} \cdot \delta_{\mathbf{i}'}) \times (\delta_{\mathbf{j}} \cdot \delta_{\mathbf{j}'}) = (\delta_{\mathbf{i}} \cdot \delta_{\mathbf{i}'}) (\epsilon_{\mathbf{j}} \cdot \epsilon_{\mathbf{j}'}) = \delta_{\mathbf{i} \oplus \mathbf{i}'} \epsilon_{\mathbf{j} \oplus \mathbf{j}'}$$

It can be easily proved that the dot-product corresponds to the usual product among sequences.

Example 3.2 Let $\mathbf{i} = (0, 1)$, $\mathbf{j} = (1, 1, 2)$, $\mathbf{i}' = (0, 0, 1)$ and $\mathbf{j}' = (0, 0)$. Then, $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}} \cdot \delta_{\mathbf{i}'\epsilon_{\mathbf{j}'}}[y(t), u(t)] = \delta_0\delta_1\epsilon_1^2\epsilon_2 \delta_0^2\delta_1\epsilon_0^2[y(t), u(t)] = \delta_0^3\delta_1^2\epsilon_0^2\epsilon_1^2\epsilon_2[y(t), u(t)] = y^3(t)y(t-1)u^2(t)u^3(t-1)u(t-2)$. Since $\mathbf{i} \oplus \mathbf{i}' = (0, 0, 0, 1, 1)$ and $\mathbf{j} \oplus \mathbf{j}' = (0, 0, 1, 1, 2)$ we can easily verify the relevant formula.

As we mentioned earlier, when we were dealing with δ -operators, the star-product corresponded to the substitution of one sequence into another. In the case of $\delta\epsilon$ -operators the star-product corresponds to the substitution of two sequences with cross-products into the "y-part" and the "u-part" respectively, of a given sequence. To clarify this concept, let us see an example. Let $z(t) = y(t-1)y(t-2)u^2(t-1) = \delta_1\delta_2\epsilon_1^2[y(t), u(t)]$ be a sequence, involving cross-products of the delays of the sequences $y(t)$ and $u(t)$. Moreover, we suppose that each of them is a cross-product of the delays of two other sequences $w(t), v(t)$: $y(t) = w^2(t-2)v(t-3) = \delta_2^2\epsilon_3[w(t), v(t)]$, $u(t) = w(t-1)v(t-1)v(t-2) = \delta_1\epsilon_1\epsilon_2[w(t), v(t)]$. By executing the substitution we get: $z(t) = w^2(t-2)w^2(t-3)w^2(t-4)v(t-2)v(t-3)v(t-4)v(t-5) = \delta_2^2\delta_3^2\delta_4^2\epsilon_2\epsilon_3\epsilon_4\epsilon_5[w(t), v(t)]$, this latter $\delta\epsilon$ -operator is the star-product of the operator $\delta_1\delta_2\epsilon_1^2$ and the pair $(\delta_2^2\epsilon_3, \delta_1\epsilon_1\epsilon_2)$. Let us present the whole subject formally. We have the $\delta\epsilon$ -operators $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$, $\delta_{\mathbf{i}_1\epsilon_{\mathbf{j}_1}}$, $\delta_{\mathbf{i}_2\epsilon_{\mathbf{j}_2}}$. Let $[w(t), v(t)] \in F \times F$ be an arbitrary given pair of causal sequences. We define the maps: $\Phi_1 : [w(t), v(t)] \rightarrow y(t) = \delta_{\mathbf{i}_1\epsilon_{\mathbf{j}_1}}[w(t), v(t)]$, $\Phi_2 : [w(t), v(t)] \rightarrow u(t) = \delta_{\mathbf{i}_2\epsilon_{\mathbf{j}_2}}[w(t), v(t)]$, $\Phi : [y(t), u(t)] \rightarrow z(t) = \delta_{\mathbf{i}\epsilon_{\mathbf{j}}}[y(t), u(t)]$. The star-product of the operator $\delta_{\mathbf{i}\epsilon_{\mathbf{j}}}$ and the pair of operators $[\delta_{\mathbf{i}_1\epsilon_{\mathbf{j}_1}}, \delta_{\mathbf{i}_2\epsilon_{\mathbf{j}_2}}]$ is the $\delta\epsilon$ -operator

$\delta_{\mathbf{h}}\epsilon_{\mathbf{s}}$, which transfers the pair $[w(t), v(t)]$ to the sequence $z(t)$. In other words, it corresponds to the map:

$$\Phi \circ (\Phi_1, \Phi_2) : [w(t), v(t)] \rightarrow z(t) = \delta_{\mathbf{h}}\epsilon_{\mathbf{s}}[w(t), v(t)]$$

Alternatively, the star-product is denoted by $\delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * [\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}, \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}]$. Of course, by using the null operators δ_e, ϵ_e we can include the star-product among simple δ -operators and $\delta\epsilon$ -operators into the above definition. For instance: $\delta_{\mathbf{i}}\epsilon_e * [\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}, \delta_e\epsilon_e] = \delta_{\mathbf{i}} * \delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}$. Let us equip the set of $\delta\epsilon$ -operators with an external operation, named addition, as follows:

$$[\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1} + \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}][y(t), u(t)] = \delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}[y(t), u(t)] + \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}[y(t), u(t)]$$

The following properties are valid for all the above operations. Their proofs are either obvious from the definitions and therefore omitted, or they can be found in [10],[18].

Proposition 3.1 (a) *The star-product is well defined.*

$$(b) \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * [\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}, \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}] = \delta_{\mathbf{i}_1+i_1}\delta_{\mathbf{i}_1+i_2}\cdots\delta_{\mathbf{i}_1+i_n}\epsilon_{\mathbf{j}_1+i_1}\epsilon_{\mathbf{j}_1+i_2}\cdots\epsilon_{\mathbf{j}_1+i_n}\delta_{\mathbf{i}_2+j_1}\delta_{\mathbf{i}_2+j_2}\cdots\delta_{\mathbf{i}_2+j_n}\epsilon_{\mathbf{j}_2+j_1}\epsilon_{\mathbf{j}_2+j_2}\cdots\epsilon_{\mathbf{j}_2+j_n} \text{ where } \mathbf{i} = (i_1, i_2, \dots, i_n) \text{ and } \mathbf{j} = (j_1, j_2, \dots, j_n)$$

$$(c) \delta_{\mathbf{i}} * (\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}) = \delta_{\mathbf{i}} * (\delta_{\mathbf{i}_1} \times \delta_{\mathbf{j}_1}) = (\delta_{\mathbf{i}} * \delta_{\mathbf{i}_1}) \times (\delta_{\mathbf{i}} * \delta_{\mathbf{j}_1}) = (\delta_{\mathbf{i}} * \delta_{\mathbf{i}_1})(\epsilon_{\mathbf{i}} * \epsilon_{\mathbf{j}_1})$$

$$(d) \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * [\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1} + \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}] \neq \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * \delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1} + \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}$$

Example 3.3 Let $\mathbf{i} = (0, 1)$, $\mathbf{j} = (1, 1, 2)$, $\mathbf{i}_1 = (0, 0, 1)$, $\mathbf{j}_1 = (1, 1)$, $\mathbf{i}_2 = (0, 1)$, $\mathbf{j}_2 = (2)$, then $\delta_{\mathbf{i}}\epsilon_{\mathbf{j}} * [\delta_{\mathbf{i}_1}\epsilon_{\mathbf{j}_1}, \delta_{\mathbf{i}_2}\epsilon_{\mathbf{j}_2}] = \delta_0\delta_1\epsilon_1^2\epsilon_2 * [\delta_0^2\delta_1\epsilon_1^2, \delta_0\delta_1\epsilon_2]$. By setting $y(t) = \delta_0^2\delta_1\epsilon_1^2[w(t), v(t)] = w^2(t)w(t-1)v^2(t-1)$, $u(t) = \delta_0\delta_1\epsilon_2[w(t), v(t)] = w(t)w(t-1)v(t-2)$ and $z(t) = \delta_0\delta_1\epsilon_1^2\epsilon_2[y(t), u(t)] = y(t)y(t-1)u^2(t-1)u(t-2)$, we finally get $z(t) = w^2(t)w^5(t-1)w^4(t-2)w(t-3)v^2(t-1)v^2(t-2)v^2(t-3)v(t-4) = \delta_0^2\delta_1^5\delta_2^4\delta_3\epsilon_1^2\epsilon_2^2\epsilon_3^2\epsilon_4[w(t), v(t)]$ and thus $\delta_0\delta_1\epsilon_1^2\epsilon_2 * [\delta_0^2\delta_1\epsilon_1^2, \delta_0\delta_1\epsilon_2] = \delta_0^2\delta_1^5\delta_2^4\delta_3\epsilon_1^2\epsilon_2^2\epsilon_3^2\epsilon_4$. Using part (b) of proposition (3.1) we get: $\delta_{(0,1)}\epsilon_{(1,1,2)} * [\delta_{(0,0,1)}\epsilon_{(1,1)}, \delta_{(0,1)}\epsilon_2] = \delta_{(0+0,0+0,1+0)}\delta_{(0+1,0+1,1+1)}\epsilon_{(1+0,1+0)}\epsilon_{(1+1,1+1)}\delta_{(0+1,1+1)}\delta_{(0+1,1+1)}\delta_{(0+2,1+2)}\epsilon_{2+1}\epsilon_{2+1}\epsilon_{2+2} = \delta_0^2\delta_1^5\delta_2^4\delta_3\epsilon_1^2\epsilon_2^2\epsilon_3^2\epsilon_4$

The $\delta\epsilon$ -polynomials are straightforward extensions of the $\delta\epsilon$ -operators that are necessary for the description of discrete non-linear systems with products among input and output sequences. These have been introduced and studied in [10],[18]. We will go over the main points, adding some new results that will clarify the ideas in the present paper. Let $\mathbf{I}_n, \mathbf{J}_m$ be sets of multi-indexes with dimensions n and m respectively. By convention we set $\mathbf{I}_0 = \mathbf{J}_0 = \{e\}$. An expression of the form:

$$A = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} \sum_{(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_n \times \mathbf{J}_m} c_{\mathbf{i}\mathbf{j}} \delta_{\mathbf{i}}\epsilon_{\mathbf{j}}$$

where $c_{\mathbf{i}\mathbf{j}}$ are real numbers, is called a $\delta\epsilon$ -polynomial. Whenever a $\delta\epsilon$ -polynomial acts on a pair of sequences, produces a polynomial of delays of those sequences, including also and products between delays of the first and second sequence, (the so-called cross-products). By means of the null index e , we can decompose a $\delta\epsilon$ -polynomial into its pure δ -part, ϵ -part and $\delta\epsilon$ -part. Indeed,

$$A_{\delta\epsilon} = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} c_{\mathbf{i}\mathbf{j}} \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} c_{\mathbf{i}\mathbf{j}} \delta_{\mathbf{i}}\epsilon_{\mathbf{j}} = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} c_{\mathbf{i}\mathbf{j}} \delta_{\mathbf{i}}\epsilon_{\mathbf{j}}$$

is the pure δ -part of A and correspondingly

$$A_\epsilon = \sum_{m=0}^{\mu} \sum_{(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_0 \times \mathbf{J}_m} c_{\mathbf{ij}} \delta_{\mathbf{i}} \epsilon_{\mathbf{j}} = \sum_{m=0}^{\mu} \sum_{\mathbf{j} \in \mathbf{J}_m} c_{e\mathbf{j}} \delta_e \epsilon_{\mathbf{j}} = \sum_{m=0}^{\mu} \sum_{\mathbf{j} \in \mathbf{J}_m} c_{\mathbf{j}} \epsilon_{\mathbf{j}}$$

the pure ϵ -part. Actually, it is a δ -polynomial acting only to inputs. The quantity $A_{\delta\epsilon} = A - A_\delta - A_\epsilon$ is the pure $\delta\epsilon$ -part. We shall call expressions of the form:

$$\sum_{(i,j) \in (\mathbf{I}_1 \times \mathbf{J}_0) \cup (\mathbf{I}_0 \times \mathbf{J}_1)} c_{ij} \delta_i \epsilon_j = \sum_{i \in \mathbf{I}_1} c_i \delta_i + \sum_{j \in \mathbf{J}_1} c_j \epsilon_j \quad (3)$$

$$\sum_{(i,j) \in (\mathbf{I}_1 \times \mathbf{J}_0)} c_{ie} \delta_i \epsilon_e = \sum_{i \in \mathbf{I}_1} c_i \delta_i, \quad \sum_{(i,j) \in (\mathbf{I}_0 \times \mathbf{J}_1)} c_{ej} \delta_e \epsilon_j = \sum_{j \in \mathbf{J}_1} c_j \epsilon_j$$

linear $\delta\epsilon$, δ and ϵ -polynomials, respectively. The term, which according to the order defined previously is ordered highly among the terms of A , is called the *maximum* term of A . By $d(A)$ we denote the minimum delay of A , in other words $d(A) = \min(\min(\mathbf{i}), \min(\mathbf{j}))$, $(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_n \times \mathbf{J}_m$, $n = 0, \dots, \nu$, $m = 0, \dots, \mu$. The largest of the numbers $\deg(\mathbf{i} + \mathbf{j})$, is called the *degree* of A , denoted also by $\deg(A)$. The equality of two $\delta\epsilon$ -polynomials is defined with the same manner with the δ -polynomials.

Example 3.4 For the polynomial: $A = 5\delta_0 + 6\delta_1 + \delta_1^2 - \delta_2\delta_3^2 + 2\epsilon_1 - 3\epsilon_2 + \epsilon_1^2 - 2\delta_1\epsilon_1 + 3\delta_1^2\epsilon_1\epsilon_2^3$ we have $\mathbf{I}_0 = \{e\}$, $\mathbf{I}_1 = \{0, 1\}$, $\mathbf{I}_2 = \{(1, 1)\}$, $\mathbf{I}_3 = \{(2, 3, 3)\}$, $\mathbf{J}_0 = \{0\}$, $\mathbf{J}_1 = \{1, 2\}$, $\mathbf{J}_2 = \{(1, 1)\}$, $\mathbf{J}_3 = \{(1, 2, 2)\}$ and $c_{0e} = 5$, $c_{1e} = 6$, $c_{(1,1)e} = 1$, $c_{(2,3,3)e} = -1$, $c_{e1} = 2$, $c_{e2} = -3$, $c_{e(1,1)} = 1$, $c_{11} = -2$, $c_{(1,1)(1,2,2)} = 3$, $c_{\mathbf{ij}} = 0$ for all the other cases. $d(A) = 0$ and $\deg(A) = \deg(\delta_1^2) + \deg(\epsilon_1\epsilon_2^3) = 6$. When this polynomial acts to a pair of sequences, we get: $A[y(t), u(t)] = 5y(t) + 6y(t-1) + y^2(t-1) - y(t-2)y(t-3)^2 + 2u(t-1) - 3u(t-2) + u^2(t-1) - 2y(t-1)u(t-1) + 3y^2(t-1)u(t-1)u^3(t-2)$.

Now, working analogously with the case of δ -polynomials we are going to define the two internal operations, the dot and the star-product for $\delta\epsilon$ -polynomials. Let

$$A = \sum_{n=0}^{\nu_1} \sum_{m=0}^{\mu_1} \sum_{(\mathbf{i}_1, \mathbf{j}_1) \in \mathbf{I}_{n,1} \times \mathbf{J}_{m,1}} a_{\mathbf{i}_1 \mathbf{j}_1} \delta_{\mathbf{i}_1} \epsilon_{\mathbf{j}_1} \quad \text{and} \quad B = \sum_{n=0}^{\nu_2} \sum_{m=0}^{\mu_2} \sum_{(\mathbf{i}_2, \mathbf{j}_2) \in \mathbf{I}_{n,2} \times \mathbf{J}_{m,2}} b_{\mathbf{i}_2 \mathbf{j}_2} \delta_{\mathbf{i}_2} \epsilon_{\mathbf{j}_2}$$

be two $\delta\epsilon$ -polynomials. Their dot-product, denoted by $A \cdot B$, is the $\delta\epsilon$ -polynomial, defined as:

$$A \cdot B = \sum_{n=0}^{\max(\nu_1, \nu_2)} \sum_{m=0}^{\max(\mu_1, \mu_2)} \sum_{(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_n \times \mathbf{J}_m} c_{\mathbf{ij}} \delta_{\mathbf{i}} \epsilon_{\mathbf{j}}$$

with $\delta_{\mathbf{i}} = \delta_{\mathbf{i}_1} \cdot \delta_{\mathbf{i}_2}$, $\epsilon_{\mathbf{j}} = \epsilon_{\mathbf{j}_1} \cdot \epsilon_{\mathbf{j}_2}$ and $c_{\mathbf{ij}} = a_{\mathbf{i}_1 \mathbf{j}_1} \cdot b_{\mathbf{i}_2 \mathbf{j}_2}$. This dot-product corresponds also to the usual product among polynomials of many variables. The star-product is also defined here as a composition of maps. Indeed, let B, C, A be $\delta\epsilon$ -polynomials. We define the maps: $B : F \times F \rightarrow F$, $[w(t), v(t)] \rightarrow y(t) = B[w(t), v(t)]$, $C : F \times F \rightarrow F$, $[w(t), v(t)] \rightarrow u(t) = C[w(t), v(t)]$, $A : F \times F \rightarrow F$, $[y(t), u(t)] \rightarrow z(t) = A[y(t), u(t)]$ The $\delta\epsilon$ -polynomial which corresponds to the composition:

$$A \circ [B, C] : F \times F \rightarrow F \quad [w(t), v(t)] \rightarrow z(t)$$

is called the star-product of the polynomials A, B, C and it is denoted by $A * [B, C]$. The above definition can be either reduced to some special cases, when B is only a δ -polynomial and C an ϵ -one, or extended to more general situations, so that substitutions of a pair of $\delta\epsilon$ -polynomials into a pair of $\delta\epsilon$ -polynomials, to be described. Details can be found at [18]. A question, which naturally arises, is how can we calculate the star-product of $\delta\epsilon$ -polynomials. There are certain formulas, [10],[18]. The most general one is presenting in [18], where we can calculate the star-product between pairs of $\delta\epsilon$ -polynomials, by means of tensor-products. Nevertheless, for the problem we study in the current paper we do not need this " huge " relation. The formulas, which are sufficient to cover all the cases we meet, are the following:

Proposition 3.2 *Let A and B be two $\delta\epsilon$ -polynomials, with $A = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} \sum_{(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_n \times \mathbf{J}_m} c_{\mathbf{ij}} \delta_{\mathbf{i}} \epsilon_{\mathbf{j}}$, then:*

- (a) $\delta_i * A = \sum_{n=0}^{\nu} \sum_{m=0}^{\mu} \sum_{(\mathbf{i}, \mathbf{j}) \in \mathbf{I}_n \times \mathbf{J}_m} c_{\mathbf{ij}} \delta_{\mathbf{i}+\mathbf{j}} \epsilon_{\mathbf{j}+\mathbf{i}}, \quad i \in \mathbf{Z}^+.$
- (b) $\delta_{\mathbf{i}} * A = (\delta_{i_1} * A) \cdot (\delta_{i_2} * A) \cdots (\delta_{i_k} * A), \quad \mathbf{i} = (i_1, i_2, \dots, i_k).$
- (c) $\delta_{\mathbf{i}} \epsilon_{\mathbf{j}} * [A, B] = (\delta_{\mathbf{i}} * A) \cdot (\epsilon_{\mathbf{j}} * B),$ where by " $\cdot$ " we denote the dot-product.
- (d) Let $\delta_{\mathbf{i}} \epsilon_{\mathbf{j}}$ be a δ -operator, with $\mathbf{i} = (i_1, i_2, \dots, i_{\varphi}), \mathbf{j} = (j_1, j_2, \dots, j_{\lambda})$ and $L = \sum_{i \in I_1} r_i \delta_i, M = \sum_{j \in J_1} m_j \epsilon_j$ linear δ and ϵ -polynomials, $I_1, J_1 \subset \mathbf{Z}$ finite sets of multindices, then

$$\delta_{\mathbf{i}} \epsilon_{\mathbf{j}} * [L, M] = \sum_{\mathbf{s} \in I_1^{\varphi}} \sum_{\mathbf{h} \in J_1^{\lambda}} r_{s_1} r_{s_2} \cdots r_{s_{\varphi}} m_{h_1} m_{h_2} \cdots m_{h_{\lambda}} \delta_{\mathbf{s}+\mathbf{i}} \epsilon_{\mathbf{h}+\mathbf{j}}$$

where $\mathbf{s} = (s_1, s_2, \dots, s_{\varphi}), \mathbf{h} = (h_1, h_2, \dots, h_{\lambda}), I_1^{\varphi}, J_1^{\lambda}$ the cartesian products $I_1^{\varphi} = \underbrace{I_1 \times I_1 \times \cdots \times I_1}_{\varphi\text{-times}}, J_1^{\lambda} = \underbrace{J_1 \times J_1 \times \cdots \times J_1}_{\lambda\text{-times}}$, and $\mathbf{s}+\mathbf{i}, \mathbf{h}+\mathbf{j}$ the common vector addition.

Proof: The proofs of (a), (b) and (c) are straightforward. We use these properties in order to show (d). Successively we have:

$$\begin{aligned} \delta_{\mathbf{i}} \epsilon_{\mathbf{j}} * [L, M] &= (\delta_{\mathbf{i}} * L) \cdot (\epsilon_{\mathbf{j}} * M) = (\delta_{i_1} * L) \cdots (\delta_{i_{\varphi}} * L) \cdot (\epsilon_{j_1} * M) \cdots (\epsilon_{j_{\lambda}} * M) = \\ &= \left(\sum_{i \in I_1} r_i \delta_{i+i_1} \right) \cdot \left(\sum_{i \in I_1} r_i \delta_{i+i_2} \right) \cdots \left(\sum_{i \in I_1} r_i \delta_{i+i_{\varphi}} \right) \cdot \left(\sum_{j \in J_1} m_j \epsilon_{j+j_1} \right) \cdot \\ &\quad \cdot \left(\sum_{j \in J_1} m_j \epsilon_{j+j_2} \right) \cdots \left(\sum_{j \in J_1} m_j \epsilon_{j+j_{\lambda}} \right) \end{aligned}$$

The given formula is nothing else than a reinstall of the above products in a compact form.

Example 3.5 (1) $\delta_1 \delta_2 \epsilon_2^2 * [2\delta_0 + \delta_1, 2\epsilon_0 - \epsilon_1] = [\delta_1 \delta_2 * (2\delta_0 + \delta_1)] \cdot [\epsilon_2^2 * (2\epsilon_0 - \epsilon_1)] = (2\delta_1 + \delta_2) \cdot (2\delta_2 + \delta_3) \cdot (2\epsilon_2 - \epsilon_3) \cdot (2\epsilon_2 - \epsilon_3) = 16\epsilon_2^2 \delta_1 \delta_2 - 16\epsilon_2 \epsilon_3 \delta_1 \delta_2 + 4\epsilon_3^2 \delta_1 \delta_2 + 8\epsilon_2^2 \delta_2^2 - 8\epsilon_2 \epsilon_3 \delta_2^2 + 2\epsilon_3^2 \delta_2^2 + 8\epsilon_2^2 \delta_1 \delta_3 - 8\epsilon_2 \epsilon_3 \delta_1 \delta_3 + 2\epsilon_3^2 \delta_1 \delta_3 + 4\epsilon_2^2 \delta_2 \delta_3 - 4\epsilon_2 \epsilon_3 \delta_2 \delta_3 + \epsilon_3^2 \delta_2 \delta_3$
(2) $(2\delta_1 \epsilon_2 + \delta_0^2 \epsilon_1 \epsilon_2) * [\delta_1 - 2\delta_2, \epsilon_0^2 \epsilon_1] = 2\delta_1 \epsilon_2 * [\delta_1 - 2\delta_2, \epsilon_0^2 \epsilon_1] + \delta_0^2 \epsilon_1 \epsilon_2 * [\delta_1 - 2\delta_2, \epsilon_0^2 \epsilon_1] = [2\delta_1 * (\delta_1 - 2\delta_2)] \cdot [\epsilon_2 * \epsilon_0^2 \epsilon_1] + [\delta_0^2 * (\delta_1 - 2\delta_2)] \cdot [\epsilon_1 \epsilon_2 * \epsilon_0^2 \epsilon_1] = 2(\delta_2 - 2\delta_3) \cdot (\epsilon_2^2 \epsilon_3) + (\delta_1 - 2\delta_2)^2 \cdot \epsilon_1^2 \epsilon_2 \cdot \epsilon_2^2 \epsilon_3 = 2\delta_2 \epsilon_2^2 \epsilon_3 - 4\delta_3 \epsilon_2^2 \epsilon_3 + \delta_1^2 \epsilon_1^2 \epsilon_2^2 \epsilon_3 - 4\delta_1 \delta_2 \epsilon_1^2 \epsilon_2^2 \epsilon_3 + 4\delta_2^2 \epsilon_1^2 \epsilon_2^2 \epsilon_3$

4 The Formal Linear Factors

In this section we present the main tool that is used throughout this paper. Actually, it is about detecting linear polynomials which can be considered as "factors" of a given $\delta\epsilon$ -polynomial with respect to the star-product and the dot-product. Specifically, let A be a concrete $\delta\epsilon$ -polynomial we write it as follows:

$$A = \sum_{\theta} \delta_0^{\kappa_{\theta}} \epsilon_0^{\sigma_{\theta}} \cdot (c_{\theta} \delta_{\mathbf{i}_{\theta}} \epsilon_{\mathbf{j}_{\theta}} * [L_{\theta}, M_{\theta}]) + \mathbf{R}_{\delta,h} + \mathbf{R}_{\epsilon,h} + R_{\delta\epsilon} \quad (4)$$

where L_{θ}, M_{θ} are linear δ and ϵ -polynomials, correspondingly, (a detailed explanation of the above expression will be given later), including the linear δ and ϵ -parts of A and $R_{\delta,h}, R_{\epsilon,h}, R_{\delta\epsilon}$ the remainders. The novelty is that some coefficients of those polynomials are not concrete numbers but undetermined parameters, which can take arbitrary values. We call these coefficients *formal coefficients* and the linear polynomials, *formal linear factors* of A . The cornerstone of the current paper is relied on the fact that by giving to these parameters proper values, we can take certain expressions of A , appropriate for solving the model matching problem.

We elucidate here that we get the expression (4) and the sets of formal linear factors by means of a symbolic algorithm. This algorithm works as follows. First it decomposes A to its δ , ϵ and $\delta\epsilon$ -parts. For each such part it finds the corresponding maximum term and then it constructs formal linear polynomials L_{θ}, M_{θ} and an operator $\delta_{\mathbf{i}_{\theta}} \epsilon_{\mathbf{j}_{\theta}}$, so that the operation $\delta_{\mathbf{i}_{\theta}} \epsilon_{\mathbf{j}_{\theta}} * [L_{\theta}, M_{\theta}]$ eliminates it. Working recursively we eliminate all the other terms but a remainder $\mathbf{R}$. This remainder is factorized with respect to the dot-product as $R = \delta_0^{\kappa} \epsilon_0^{\sigma} \cdot \tilde{R}$ and then we repeat the whole procedure, working with $\tilde{R}$. To establish certain definitions to a more rigorous way we need first to present the said algorithm.

The Formal Linear Factors (FLF) - Algorithm.

Input: A $\delta\epsilon$ -polynomial A with no constant terms.

Output: The quantity h^* , the sets $\mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$ and the polynomials $R_{\delta,\nu}, R_{\epsilon,\nu}, \nu = 0, 1, \dots, h^*, R_{\delta\epsilon,h^*}$.

STEP 0: Set $h = 0, \mathcal{L} = \{\}, \mathcal{M} = \{\}, \mathcal{C} = \{\}, \mathcal{O} = \{\}$.

STEP 1: Decompose A as follows: $A = A_{\delta} + A_{\epsilon} + A_{\delta\epsilon}$, where $A_{\delta}, A_{\epsilon}, A_{\delta\epsilon}$ are the pure δ -part, ϵ -parts and $\delta\epsilon$ -parts of A , respectively.

STEP 2: Set $u = 1, \omega = 0$. **REPEAT** the following substeps **UNTIL** $A_{\delta} = 0$ or A_{δ} is a polynomial of the variable δ_0 only.

SUBSTEP 2a: **CALL SUBROUTINE REMAINDER** with inputs $A_{\delta}, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}, h, u, \omega$ and outputs $R, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$.

SUBSTEP 2b: Find the maximum integer $\theta \geq 0$ such that $R = \delta_0^{\theta} \cdot \tilde{R}$ and $\tilde{R}$ is a δ -polynomial, not containing a constant term.

SUBSTEP 2c: Set $A_{\delta} = \tilde{R}, u = u + 1$.

END OF THE REPEAT

STEP 3: Rename the last value A_{δ} as $R_{\delta,h}$.

STEP 4: Set $u = 0, \omega = 1$. **REPEAT** the following substeps **UNTIL** $A_{\epsilon} = 0$ or A_{ϵ} is a

SUBSTEP 4a: CALL SUBROUTINE REMAINDER with input $A_\epsilon, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}, h, u, \omega$ and outputs $R, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$.

SUBSTEP 4b: Find the maximum integer $\rho \geq 0$ such that $R = \epsilon_0^\rho \cdot \tilde{R}$ and $\tilde{R}$ is an ϵ -polynomial, not containing a constant term.

SUBSTEP 4c: Set $A_\epsilon = \tilde{R}$, $\omega = \omega + 1$.

END OF THE REPEAT

STEP 5: Rename the last value A_ϵ as $R_{\epsilon, h}$.

STEP 6: IF $A_{\delta\epsilon} = 0$ or $A_{\delta\epsilon}$ is a polynomial of the variables δ_0 and ϵ_0 only THEN set $R_{\delta\epsilon, h} = A_{\delta\epsilon}$, $h^* = h$ and goto the **Output** ELSE proceed.

STEP 7: Set $u = 0, \omega = 0$, CALL SUBROUTINE REMAINDER with input $A_{\delta\epsilon}, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}, h, u, \omega$ and outputs $R, \mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$.

STEP 8: Find the maximum integers $\kappa, \sigma \geq 0$ such that $R = \delta_0^\kappa \epsilon_0^\sigma \cdot \tilde{R}$ and $\tilde{R}$ is a $\delta\epsilon$ -polynomial, not containing a constant term.

STEP 9: Set $A = \tilde{R}$, $h = h + 1$, goto step 1.

SUBROUTINE REMAINDER.

Input: A $\delta\epsilon$ -polynomial A , the sets $\mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$ and the counters h, u, ω .

Output: The polynomial R . The sets $\mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}$.

REM-STEP 0: Set $\lambda = 0, R = A$.

REM-STEP 1: We decompose R as follows: $R = R_l + R_{nl}$ where R_l, R_{nl} are the linear and the non-linear parts of R , respectively.

REM-STEP 2: IF $R_l \neq 0$ THEN IF $u = 1$ THEN set $L_{0, u, h} = R_l$, $c_{0, u, \omega, h} = 1$, $\mathcal{O} = \mathcal{O} \cup \{\delta_0\}$, $\mathcal{C} = \mathcal{C} \cup \{1\}$, $\mathcal{L} = \mathcal{L} \cup \{L_{0, u, h}\}$ ELSE set $M_{0, \omega, h} = R_l$, $c_{0, u, \omega, h} = 1$, $\mathcal{O} = \mathcal{O} \cup \{\delta_0\}$, $\mathcal{C} = \mathcal{C} \cup \{1\}$, $\mathcal{M} = \mathcal{M} \cup \{M_{0, \omega, h}\}$ ELSE proceed.

REM-STEP 3: Set $R = R_{nl}$ REPEAT the following REM-substeps UNTIL $R_\lambda = 0$ or all the terms of R_λ become zero terms (i.e. terms of the form $\delta_0 \delta_{i_2} \cdots \delta_{i_n} \epsilon_0 \epsilon_{j_1} \cdots \epsilon_{j_m}$, $0 \leq i_2 \leq \cdots \leq i_n, 0 \leq j_2 \leq \cdots \leq j_m$).

REM-Substep 3a: $\lambda = \lambda + 1, R_{\lambda-1} = R$

REM-Substep 3b: Let $c_{\lambda, u, \omega, h} \delta_{i_{\lambda, u, \omega, h}} \epsilon_{j_{\lambda, u, \omega, h}} = c_{\lambda, u, \omega, h} \delta_{i_1} \delta_{i_2} \cdots \delta_{i_n} \epsilon_{j_1} \epsilon_{j_2} \cdots \epsilon_{j_m}$ be the *maximum* non-zero term of $R_{\lambda-1}$, $0 \leq i_1 \leq i_2 \leq \cdots \leq i_n, 0 \leq j_1 \leq j_2 \leq \cdots \leq j_m$ and $c_{\lambda, u, \omega, h}$ its coefficient. (Actually, in the first iteration of the algorithm, $c_{\lambda, u, \omega, h}$ is always a real number. It then becomes a function of the unknown parameters $w_{i, j, k, h}, s_{i, j, k, h}$.)

REM-Substep 3c: IF $\delta_{i_{\lambda, u, \omega, h}} \neq \delta_e$ THEN we form the formal linear δ -polynomial

$$L_{\lambda, u, h} = w_{\lambda, u, h, 0} \delta_0 + w_{\lambda, u, h, 1} \delta_1 + w_{\lambda, u, h, 2} \delta_2 + \cdots + \delta_{i_1}$$

where $w_{\lambda, u, h, 0}, w_{\lambda, u, h, 1}, \dots$ are unknown parameters, taking values in $\mathbf{R}$ and i_1 is the minimum delay of the δ -part of the maximum term ELSE $L_{\lambda, u, h} = \delta_e$

REM-Substep 3d: IF $\epsilon_{j_{\lambda, u, \omega, h}} \neq \epsilon_e$ THEN we form the formal linear ϵ -polynomial

where $s_{\lambda,\omega,h,0}, s_{\lambda,\omega,h,1}, \dots$ are unknown parameters that take values in $\mathbf{R}$ and j_1 is the minimum delay of the ϵ -part of the maximum term **ELSE**
 $M_{\lambda,\omega,h} = \epsilon_e$

REM-Substep 3e: We execute the operation:

$$\begin{aligned} R_\lambda &= R_{\lambda-1} - c_{\lambda,u,\omega,h} \delta_0 \delta_{i_2-i_1} \cdots \delta_{i_n-i_1} \epsilon_0 \epsilon_{j_2-j_1} \cdots \epsilon_{j_m-j_1} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}] = \\ &= R_{\lambda-1} - c_{\lambda,u,\omega,h} \delta_{i_{\lambda,u,\omega,h}} \epsilon_{j_{\lambda,u,\omega,h}} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}] \end{aligned}$$

REM-Substep 3f: For $L_{\lambda,u,h} \neq \delta_e$, $M_{\lambda,\omega,h} \neq \epsilon_e$ we set $\mathcal{L} = \mathcal{L} \cup \{L_{\lambda,u,h}\}$,
 $\mathcal{M} = \mathcal{M} \cup \{M_{\lambda,\omega,h}\}$, $\mathcal{C} = \mathcal{C} \cup \{c_{\lambda,u,\omega,h}\}$, $\mathcal{O} = \mathcal{O} \cup \{\delta_{i_{\lambda,u,\omega,h}} \epsilon_{j_{\lambda,u,\omega,h}}\}$

END OF THE REPEAT

REM-STEP 4: Rename the last value of R_λ as R and go to the **Output**.

The following definitions will play a crucial role in the context of the model matching problem, below. First of all the sets $\mathcal{L}$ and $\mathcal{M}$, which are formed from all the linear δ and ϵ -polynomials that appear in the above algorithm, are called 'the sets of the Formal δ -Linear Factors' and 'the Formal ϵ -Linear Factors of A ', respectively. We must note here that the use of the word Formal is a little bit excessive, since all the elements of the sets $\mathcal{L}$ and $\mathcal{M}$ are not formal linear polynomials. The linear δ and ϵ -parts of A , usually denoted by $A_{\delta,l}, A_{\epsilon,l}$, are a first example. The linear polynomial R_l , appeared in REM-STEP 1 is another. By $\mathcal{L}^*$ and $\mathcal{M}^*$ we name the sets $\mathcal{L}^* = \mathcal{L} - \{A_{\delta,l}\}$, $\mathcal{M}^* = \mathcal{M} - \{A_{\epsilon,l}\}$, $\mathcal{L}_\delta$ is the set of the linear factors of the δ -part of A , in other words $\mathcal{L}_\delta = \{L_{\lambda,u,0}\} \subset \mathcal{L}$ (it includes $A_{\delta,l}$), $\overline{\mathcal{L}}, \overline{\mathcal{M}}$ are the sets of the δ or ϵ -linear factors of A which do not participate to any cross-product, i.e. $\overline{\mathcal{L}} = \{L_{\lambda,u,h}, u \neq 0\}$, $\overline{\mathcal{M}} = \{M_{\lambda,\omega,h}, \omega \neq 0\}$, finally $\overline{\mathcal{L}}^* = \overline{\mathcal{L}} - \{A_{\delta,l}\}$, $\overline{\mathcal{M}}^* = \overline{\mathcal{M}} - \{A_{\epsilon,l}\}$. The coefficient $c_{\lambda,u,\omega,h}$ is called the *companion coefficient* of the polynomial $L_{\lambda,u,h}$ or of the polynomial $M_{\lambda,\omega,h}$ and it is denoted by $c_{coef}(L_{\lambda,u,h})$ or $c_{coef}(M_{\lambda,\omega,h})$. By convention, $c_{coef}(L_{0,u,h}) = c_{coef}(M_{0,\omega,h}) = 1$ for any u and h . The set of all companion coefficients is denoted by $\mathcal{C}$. The polynomials $R_{\delta,\nu}, R_{\epsilon,\nu}, \nu = 0, 1, \dots, h^*$, $R_{\delta\epsilon,h^*}$ are called the δ, ϵ and $\delta\epsilon$ -remainders, correspondingly and the set $\mathcal{O}$ the set of the formal $\delta\epsilon$ -operators. Let $\mathcal{A} \subseteq \mathcal{L} \cup \mathcal{M}$, be a set consisting from some δ or ϵ -linear factors of A . By $\mathcal{C}^{\mathcal{A}} \subseteq \mathcal{C}$ we denote the set of the companion coefficients of the elements of $\mathcal{A}$. That is $\mathcal{C}^{\mathcal{A}} = \{c_{\lambda,u,\omega,h} \in \mathcal{C} : c_{\lambda,u,\omega,h} \text{ is the companion coefficient of an element of } \mathcal{A}\}$. The next theorems describe the behaviour of the FLF-Algorithm.

Theorem 4.1 *The FLF-Algorithm terminates after a finite number of steps.*

Proof: A glance at the algorithm indicates that essentially, it consists from three repeat-loops, appeared at the steps 2,4 and the REM-step 3 and a loop defined between the steps 1 and 9. The termination of those loops ensure the termination of the algorithm. Let A be an input of the Remainder-Subroutine. As we pass from the REM-substep 3e we get: $R_{new} = R_{previous} - c_{\lambda,u,\omega,h} \delta_{i_{\lambda,u,h}} \epsilon_{j_{\lambda,\omega,h}} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}]$, where $c_{\lambda,u,\omega,h}$ is the current maximum non zero term. By means of proposition 3.2 (d), we get:

$$\delta_{i_{\lambda,u,h}} \epsilon_{j_{\lambda,\omega,h}} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}] = \delta_0 \delta_{i_2-i_1} \cdots \delta_{i_n-i_1} \epsilon_0 \epsilon_{j_2-j_1} \cdots \epsilon_{j_m-j_1} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}] =$$

$$= \delta_{i_1} \delta_{i_2} \cdots \delta_{i_n} \epsilon_{j_1} \epsilon_{j_2} \cdots \epsilon_{j_m} + \text{other terms}$$

Therefore, the above substraction will eliminate this $\delta_{i_{\lambda,u,h}} \epsilon_{j_{\lambda,\omega,h}}$ term. The construction of the linear polynomial $L_{\lambda,u,h}, M_{\lambda,\omega,h}$ guarantees that all the terms of R_{new} will be ordered lower than $\delta_i \epsilon_j$, thus, by repeating the same procedure for those terms, we shall gradually eliminate all the non zero terms of A and the REMAINDER SUBROUTINE will terminate. Let R be the output of this subroutine. It will be consist of terms of the form: $\delta_0 \delta_k \epsilon_o \epsilon_h$. Factorizing it by powers of $\delta_0 \epsilon_0$ (steps 2b,4b,8) we decrease the degree of R at least by two. This nesting ensures the termination of all the loops and consequently the termination of the algorithm.

Theorem 4.2 *Let A be a given $\delta\epsilon$ -polynomial and $A_{l,\delta}, A_{l,\epsilon}$ its linear δ and ϵ -parts. Let $\mathcal{L}, \mathcal{M}, \mathcal{C}, \mathcal{O}, h^*$ and $R_{\delta\epsilon,h^*}, R_{\delta,h}, R_{\epsilon,h}, h = 0, \dots, h^*$ be the outputs of the FLF-Algorithm, after its application to a given $\delta\epsilon$ -polynomial A . Then,*

$$A = \sum_{h=0}^{h^*} \sum_{\omega=0}^{\omega_h^*} \sum_{u=0}^{u_h^*} \sum_{\lambda=0}^{v_{u,\omega,h}} \delta_0^{\kappa_{u,h}} \epsilon_0^{\sigma_{\omega,h}} \cdot (c_{\lambda,u,\omega,h} \delta_{i_{\lambda,u,\omega,h}} \epsilon_{j_{\lambda,u,\omega,h}} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}]) + \mathbf{R}_{\delta,h} + \mathbf{R}_{\epsilon,h} + R_{\delta\epsilon,h^*} \quad (5)$$

where $\omega_h^*, u_h^*, v_{u,\omega,h}, \kappa_{u,h}, \sigma_{\omega,h}$ are positive integers, depending from the values of h, u and ω , $c_{\lambda,u,\omega,h} \in \mathcal{C}$, $\delta_{i_{\lambda,u,\omega,h}} \epsilon_{j_{\lambda,u,\omega,h}} \in \mathcal{O}$, $L_{\lambda,u,h} \in \mathcal{L}$, $M_{\lambda,\omega,h} \in \mathcal{M}$ and the following "border" conditions hold: $\kappa_{1,h} = 0$, $\kappa_{0,0} = 0$, $\sigma_{1,h} = 0$, $\sigma_{0,0} = 0$, $c_{0,0,\omega,h} = 1$, $c_{0,u,0,h} = 1$, $c_{0,0,0,h} = 0$, $c_{\lambda,u,\omega,h} = 0$ for $u + \omega > 1$, $\delta_{i_{0,u,0,h}} = \delta_0$, $\delta_{i_{\lambda,0,\omega,h}} = \delta_e$, $\epsilon_{j_{0,0,\omega,h}} = \epsilon_0$, $\epsilon_{j_{\lambda,0,\omega,h}} = \epsilon_e$, for $u = 1, \dots, u_h^*$, $\omega = 1, \dots, \omega_h^*$, $\lambda = 0, \dots, v_{u,\omega,h}$, $h = 0, \dots, h^* - 1$ and $L_{0,1,0} = A_{\delta,l}$, $M_{0,1,0} = A_{\epsilon,l}$. Furthermore, this expression is feasible for any $\delta\epsilon$ -polynomial A and unique, under the assumption that the parameters $w_{\lambda,u,h,k}, s_{\lambda,\omega,h,k}$ are considered as constants.

Proof: Using reverse recursive relations we can write the evolution of the FLF-Algorithm in a condensed form. Let us denote by H_h the outcome of the loop, defined by steps 1 and 9, at any specific iteration h , $\Delta_{u,h}$ the outcome of the repeat procedure in step 2, and $E_{\omega,h}$ the outcome at the repeat procedure in step 4. It can be easily proved that the next equalities hold:

$$H_h = \Delta_{1,h} + E_{1,h} + \sum_{\lambda=1}^{\nu_h} c_{\lambda,0,0,h} \delta_{i_{\lambda,0,0,h}} \epsilon_{j_{\lambda,0,0,h}} * [L_{\lambda,0,h}, M_{\lambda,0,h}] + \delta_0^{\kappa_{u,h+1}} \epsilon_0^{\sigma_{\omega,h+1}} \cdot H_{h+1} \quad , \quad h = 0, 1, \dots, h^* - 1$$

$$\Delta_{u,h} = L_{0,u,h} + \sum_{\lambda=1}^{g_{u,h}} c_{\lambda,u,0,h} \delta_{i_{\lambda,u,h}} * L_{\lambda,u,h} + \delta_0^{k_{u,h}} \cdot \Delta_{u+1,h} \quad , \quad u = 1, \dots, u_h^*$$

$$E_{\omega,h} = M_{0,\omega,h} + \sum_{\lambda=1}^{\gamma_{\omega,h}} c_{\lambda,0,\omega,h} \epsilon_{j_{\lambda,\omega,h}} * M_{\lambda,\omega,h} + \epsilon_0^{\sigma_{\omega,h}} \cdot E_{\omega+1,h} \quad , \quad \omega = 1, \dots, \omega_h^*$$

with terminal conditions $H_{h^*} = R_{\delta\epsilon,h^*}$, $\Delta_{u_h^*+1,h} = R_{\delta,h}$, $E_{\omega_h^*+1,h} = R_{\epsilon,h}$, $h = 0, 1, \dots, h^*$, $\nu_h, g_{u,h}, \gamma_{\omega,h}$ are positive integers, depending from the quantities h, u, ω . Obviously $A = H_0$. Expanding this relation in details we take:

$$A = L_{0,1,0} + \sum_{\lambda=1}^{g_{1,0}} c_{\lambda,1,0,0} \delta_{i_{\lambda,1,0}} * L_{\lambda,1,0} + \delta_0^{k_{1,0}} \cdot (L_{0,2,0} + \sum_{\lambda=1}^{g_{2,0}} c_{\lambda,2,0,0} \delta_{i_{\lambda,2,0}} * L_{\lambda,2,0} + \delta_0^{k_{2,0}} \cdot ($$

$$\begin{aligned}
& \cdots \delta_0^{k_{u_0^*,0}-1,0} \cdot (L_{0,u_0^*,0} + \sum_{\lambda=1}^{g_{u_0^*,0}} c_{\lambda,u_0^*,0,0} \delta_{\mathbf{i}_{\lambda,u_0^*,0}} * L_{\lambda,u_0^*,0} + R_{\delta,0}) \cdots) + M_{0,1,0} + \sum_{\lambda=1}^{\gamma_{1,0}} c_{\lambda,0,1,0} \\
& \epsilon_{\mathbf{j}_{\lambda,1,0}} * M_{\lambda,1,0} + \epsilon_0^{\sigma_{1,0}} \cdot (M_{0,2,0} + \sum_{\lambda=1}^{\gamma_{2,0}} c_{\lambda,0,2,0} \epsilon_{\mathbf{j}_{\lambda,2,0}} * M_{\lambda,2,0} + \epsilon_0^{\sigma_{2,0}} \cdot (\cdots \epsilon_0^{\sigma_{\omega_0^*,0}-1,0} \cdot (M_{0,\omega_0^*,0} + \\
& + \sum_{\lambda=1}^{\gamma_{\omega_0^*,0}} c_{\lambda,0,\omega_0^*,0} \epsilon_{\mathbf{j}_{\lambda,\omega_0^*,0}} * M_{\lambda,\omega_0^*,0} + R_{\epsilon,0})) \cdots) + \sum_{\lambda=1}^{\nu_0} c_{\lambda,0,0,0} \delta_{\mathbf{i}_{\lambda,0,0,0}} \epsilon_{\mathbf{j}_{\lambda,0,0,0}} * [L_{\lambda,0,0}, M_{\lambda,0,0}] + \\
& + \delta_0^{k_{0,1}+1} \epsilon_0^{\sigma_{0,1}} \cdot (L_{0,1,1} + \sum_{\lambda=1}^{g_{1,1}} c_{\lambda,1,0,1} \delta_{\mathbf{i}_{\lambda,1,1}} * L_{\lambda,1,1} + \delta_0^{k_{1,1}} \cdot (L_{0,2,1} + \sum_{\lambda=1}^{g_{2,1}} c_{\lambda,2,0,1} \delta_{\mathbf{i}_{\lambda,2,1}} * L_{\lambda,2,1} + \delta_0^{k_{2,1}} \cdot (\\
& \cdots \delta_0^{k_{u_1^*,1}-1,1} \cdot (L_{0,u_1^*,1} + \sum_{\lambda=1}^{g_{u_1^*,1}} c_{\lambda,u_1^*,0,1} \delta_{\mathbf{i}_{\lambda,u_1^*,1}} * L_{\lambda,u_1^*,1} + R_{\delta,1})) \cdots) + M_{0,1,1} + \sum_{\lambda=1}^{\gamma_{1,1}} c_{\lambda,0,1,1} \epsilon_{\mathbf{j}_{\lambda,1,1}} * M_{\lambda,1,1} + \\
& + \epsilon_0^{\sigma_{1,1}} \cdot (M_{0,2,1} + \sum_{\lambda=1}^{\gamma_{2,1}} c_{\lambda,0,2,1} \epsilon_{\mathbf{j}_{\lambda,2,1}} * M_{\lambda,2,1} + \epsilon_0^{\sigma_{2,1}} (\cdots \epsilon_0^{\sigma_{\omega_1^*,1}-1,1} (M_{0,\omega_1^*,1} + \sum_{\lambda=1}^{\gamma_{\omega_1^*,1}} c_{\lambda,0,\omega_1^*,1} \epsilon_{\mathbf{j}_{\lambda,\omega_1^*,1}} * M_{\lambda,\omega_1^*,1} + \\
& + R_{\epsilon,1})) \cdots) + \sum_{\lambda=1}^{\nu_1} c_{\lambda,0,0,1} \delta_{\mathbf{i}_{\lambda,0,0,1}} \epsilon_{\mathbf{j}_{\lambda,0,0,1}} * [L_{\lambda,0,1}, M_{\lambda,0,1}] + \delta_0^{k_{0,2}} \epsilon_0^{\sigma_{0,2}} (\cdots \cdots L_{0,1,h^*-1} + \sum_{\lambda=1}^{g_{1,h^*-1}} c_{\lambda,1,0,h^*-1} \\
& \delta_{\mathbf{i}_{\lambda,1,h^*-1}} * L_{\lambda,1,h^*-1} + \delta_0^{k_{1,h^*-1}} (L_{0,2,h^*-1} + \sum_{\lambda=1}^{g_{2,h^*-1}} c_{\lambda,2,0,h^*-1} \delta_{\mathbf{i}_{\lambda,2,h^*-1}} * L_{\lambda,2,h^*-1} + \delta_0^{k_{2,h^*-1}} (\\
& \cdots \delta_0^{k_{u_{h^*-1}^*}-1,h^*-1} (L_{0,u_{h^*-1}^*,h^*-1} + \sum_{\lambda=1}^{g_{u_{h^*-1}^*,h^*-1}} c_{\lambda,u_{h^*-1}^*,0,h^*-1} \delta_{\mathbf{i}_{\lambda,u_{h^*-1}^*,h^*-1}} * L_{\lambda,u_{h^*-1}^*,h^*-1} + R_{\delta,h^*-1})) \cdots \\
&) + M_{0,1,h^*-1} + \sum_{\lambda=1}^{\gamma_{1,h^*-1}} c_{\lambda,0,1,h^*-1} \epsilon_{\mathbf{j}_{\lambda,1,h^*-1}} * M_{\lambda,1,h^*-1} + \epsilon_0^{\sigma_{1,h^*-1}} (M_{0,2,h^*-1} + \sum_{\lambda=1}^{\gamma_{2,h^*-1}} c_{\lambda,0,2,h^*-1} \epsilon_{\mathbf{j}_{\lambda,2,h^*-1}} * \\
& * M_{\lambda,2,h^*-1} + \epsilon_0^{\sigma_{2,h^*-1}} (\cdots \epsilon_0^{\sigma_{\omega_{h^*-1}^*}-1,h^*-1} (M_{0,\omega_{h^*-1}^*,h^*-1} + \sum_{\lambda=1}^{\gamma_{\omega_{h^*-1}^*,h^*-1}} c_{\lambda,0,\omega_{h^*-1}^*,h^*-1} \epsilon_{\mathbf{j}_{\lambda,\omega_{h^*-1}^*,h^*-1}} * \\
& * M_{\lambda,\omega_{h^*-1}^*,h^*-1} + R_{\epsilon,h^*-1})) \cdots) + \\
& + \sum_{\lambda=1}^{\nu_{h^*}-1} c_{\lambda,0,0,h^*-1} \delta_{\mathbf{i}_{\lambda,0,0,h^*-1}} \epsilon_{\mathbf{j}_{\lambda,0,0,h^*-1}} * [L_{\lambda,0,h^*-1}, M_{\lambda,0,h^*-1}] + R_{\delta,\epsilon,h^*})) \cdots) \cdots) \quad (6)
\end{aligned}$$

Rewriting (6) in a proper compact manner and renaming the quantities $g_{u,h}$, $\gamma_{u,h}$ as $v_{u,\omega,h}$, we take the relation (5) upon proving. Now, let A be an arbitrary $\delta\epsilon$ -polynomial. If it is

$L_{0,1,0} = A_{\delta,l}$, $M_{0,1,0} = A_{\epsilon,l}$, $c_{\lambda,u,\omega,h} = 0$ $h, \lambda \neq 0$, $u, \omega \neq 1$ and putting the remainders equal to zero. If A is nonlinear but contains only $\delta_0 \epsilon_0$ -terms, then we put $R_{\delta\epsilon,h^*} = A$ and $c_{\lambda,u,\omega,h} = 0$. In all the other cases we have a maximum term and therefore the FLF-Algorithm can be applied. All the above supports the feasibility of the method. Let us now deal with the uniqueness question. We explain first that by the expression "are considered as constants" we mean that we treat the parameters like to be specific number. Now, if A has only zero terms or it is linear then the proof of the theorem is trivial. Let us suppose that A contains non-zero terms and that, for the sake of proof, $\psi_a \delta_{\mathbf{i}_a} \epsilon_{\mathbf{j}_a}$, $\psi_a \in \mathbf{R}$ with $\mathbf{i}_a = (i_{1,a}, i_{2,a}, \dots, i_{n,a})$, $\mathbf{j}_a = (j_{1,a}, j_{2,a}, \dots, j_{m,a})$, is its maximum term. Let us further suppose, for the sake of simplicity, that the second higher ordered term of A is $\psi_\beta \delta_{\mathbf{i}_\beta} \epsilon_{\mathbf{j}_\beta}$, $\psi_\beta \in \mathbf{R}$ with $\mathbf{i}_\beta = (i_{1,\beta}, i_{2,\beta}, \dots, i_{n,\beta})$, $\mathbf{j}_\beta = (j_{1,\beta}, j_{2,\beta}, \dots, j_{m,\beta})$ and $j_{m,\beta} = j_{m,a} - 1$. As we pass from the REM-Step 3e for the first time we get: $R_1 = A - c_{1,0,0,0} \delta_{\mathbf{i}_{1,0,0,0}} \epsilon_{\mathbf{j}_{1,0,0,0}} * [L_{1,0,0}, M_{1,0,0}]$ and thus $A = R_1 + c_{1,0,0,0} \delta_{\mathbf{i}_{1,0,0,0}} \epsilon_{\mathbf{j}_{1,0,0,0}} * [L_{1,0,0}, M_{1,0,0}]$. But $\delta_{\mathbf{i}_{1,0,0,0}} \epsilon_{\mathbf{j}_{1,0,0,0}} = \delta_0 \delta_{i_{2,a}-i_{1,a}} \cdots \delta_{i_{n,a}-i_{1,a}} \epsilon_0 \epsilon_{j_{2,a}-j_{1,a}} \cdots \epsilon_{j_{m,a}-j_{1,a}}$ and $L_{1,0,0} = w_{1,0,0,0} \delta_0 + w_{1,0,0,1} \delta_1 + \cdots + \delta_{i_{1,a}}$, $M_{1,0,0} = s_{1,0,0,0} \epsilon_0 + s_{1,0,0,1} \epsilon_1 + \cdots + \epsilon_{j_{1,a}}$. By means of proposition (3.2), (d), we can see that $c_{1,0,0,0} \delta_{\mathbf{i}_{1,0,0,0}} \epsilon_{\mathbf{j}_{1,0,0,0}} * [L_{1,0,0}, M_{1,0,0}] = c_{1,0,0,0} \delta_{i_{1,a}} \delta_{i_{2,a}} \cdots \delta_{i_{n,a}} \epsilon_{j_{1,a}} \epsilon_{j_{2,a}} \cdots \epsilon_{j_{m,a}} + c_{1,0,0,0} (s_{1,0,0,j_{m,a}-1}) \delta_{i_{1,a}} \delta_{i_{2,a}} \cdots \delta_{i_{n,a}} \epsilon_{j_{1,a}} \epsilon_{j_{2,a}} \cdots \epsilon_{j_{m,a}-1} + \text{other terms} = c_{1,0,0,0} \delta_{\mathbf{i}_a} \epsilon_{\mathbf{j}_a} + c_{1,0,0,0} (s_{1,0,0,j_{m,a}-1}) \delta_{\mathbf{i}_\beta} \epsilon_{\mathbf{j}_\beta} + \text{other terms}$. By equating the coefficients we take that $c_{1,0,0,0} = \psi_a$, hence $c_{1,0,0,0}$ is uniquely determined. Now, the maximum term appeared into R_1 is $\delta_{\mathbf{i}_\beta} \epsilon_{\mathbf{j}_\beta}$. A second visit at the REM-Step 3e will give $R_1 = R_2 + c_{2,0,0,0} \delta_{\mathbf{i}_{2,0,0,0}} \epsilon_{\mathbf{j}_{2,0,0,0}} * [L_{2,0,0}, M_{2,0,0}]$. Working exactly as before we shall finally get that $c_{2,0,0,0} = \psi_\beta - c_{1,0,0,0} (s_{1,0,0,j_{m,a}-1})$. Since this expression is a function of $c_{1,0,0,0}$ and of some parameters w_{ijk}, s_{ijk} considered as constants, we conclude that $c_{2,0,0,0}$ is also defined uniquely. By induction, we can then see that all the coefficients are uniquely determined. The polynomials $R_{\delta,h}, R_{\epsilon,h}, R_{\delta\epsilon,h^*}$ consist only of zero terms. These terms arise either from the polynomial A or from the products $c_{\lambda,u,\omega,h} \delta_{\mathbf{i}_{\lambda,u,\omega,h}} \epsilon_{\mathbf{j}_{\lambda,u,\omega,h}}$. The unique determination of the coefficients $c_{\lambda,u,\omega,h}$ entails the uniqueness of the remainders and, thus, the theorem has been proved. $\square$

Remark 4.1 *The equation (5) can be written shortly as:*

$$\sum_{\theta} \delta_0^{\kappa_\theta} \epsilon_0^{\sigma_\theta} \cdot (c_\theta \delta_{\mathbf{i}_\theta} \epsilon_{\mathbf{j}_\theta} * [L_\theta, M_\theta]) + \mathbf{R}_{\delta,h} + \mathbf{R}_{\epsilon,h} + R_{\delta\epsilon}$$

with θ is an abbreviation for the vector: (λ, u, ω, h) .

Let A be a $\delta\epsilon$ -polynomial, $\mathcal{L}, \mathcal{M}$, its sets of the Formal Linear Factors. and $\mathcal{C}$ the set of the companion coefficients. The elements of these sets, or of any subset of them, can be transformed to specific δ or ϵ -linear polynomials or to specific companion coefficients, by giving to the parameters $w_{\lambda,u,h,k}$, $s_{\lambda,u,h,k}$ concrete values, according to a set of substitution rules. In this case we say that $\mathcal{L}, \mathcal{M}$ and $\mathcal{C}$ are evaluated over a set of rules U , thus writing: $\mathcal{L} \big|_U$, $\mathcal{M} \big|_U$ and $\mathcal{C} \big|_U$. More rigorously, let $\mathbf{W} = (w_{\lambda,i,h,k})$ be the set of the w -parameters, written as a vector and $\mathbf{r} = (a_{\lambda,i,h,k})$ a vector of real numbers, which is in one-to-one correspondence with the vector $\mathbf{W}$. We say that these parameters follow the rule $\mathbf{r}$, thus writing $\mathbf{W} \rightarrow \mathbf{r}$, if the following substitutions are valid $w_{\lambda,i,h,k} = a_{\lambda,i,h,k}$. The set $\mathcal{L} \big|_{\mathbf{r}}$ is defined as follows:

$$\mathcal{L} \big|_{\mathbf{r}} = \{ L_{\lambda,u,\omega,h} = \sum_{i=0}^{a_\lambda-1} w_{\lambda,u,\omega,h,i} \delta_i + \delta_{a_\lambda} \mid h=0, h^*, \omega=1, \omega^* \}$$

$\lambda = 1, \dots, \lambda_{u,h}^*$ and a_λ positive integers , with $\mathbf{W} = (w_{\lambda,u,h,k}) \rightarrow \mathbf{r}$

Let N be a set of rules $N = \{\mathbf{r}_1, \mathbf{r}_2, \dots, \mathbf{r}_\psi\}$ then $\mathcal{L} \big|_N = \{ \mathcal{L} \big|_{\mathbf{r}_1}, \mathcal{L} \big|_{\mathbf{r}_2}, \dots, \mathcal{L} \big|_{\mathbf{r}_\psi} \}$ Simultaneously, if $\mathbf{S} = (s_{\lambda,j,h,k})$ is the vector of the s -parameters and $\mathbf{q} = (b_{\lambda,j,h,k})$ a vector of real numbers, which is in one-to-one correspondence with the vector $\mathbf{S}$. We say that these parameters follow the rule $\mathbf{q}$, thus writing $\mathbf{S} \rightarrow \mathbf{q}$, if the following substitutions are valid $s_{\lambda,j,h,k} = b_{\lambda,j,h,k}$. We define

$$\mathcal{M} \big|_{\mathbf{q}} = \{M_{\lambda,\omega,h} = \sum_{k=0}^{b_\lambda-1} s_{\lambda,\omega,h,k} \epsilon_k + \epsilon_{b_\lambda} \quad , \quad h = 0, \dots, h^*, \omega = 1, \dots, \omega_h^*,$$

$\lambda = 1, \dots, \lambda_{\omega,h}^*$ and b_λ positive integers , with, $\mathbf{S} = (s_{\lambda,\omega,h,k}) \rightarrow \mathbf{q}$

Let Q be the set of rules $Q = \{\mathbf{q}_1, \mathbf{q}_2, \dots, \mathbf{q}_\mu\}$, then $\mathcal{M} \big|_Q = \{ \mathcal{M} \big|_{\mathbf{q}_1}, \mathcal{M} \big|_{\mathbf{q}_2}, \dots, \mathcal{M} \big|_{\mathbf{q}_\mu} \}$. If w and s -parameters appear together, then we say that they follow the rule $(\mathbf{r}, \mathbf{q})$, thus writing $(\mathbf{W}, \mathbf{S}) \rightarrow (\mathbf{r}, \mathbf{q})$, if $w_{\lambda,i,h,k} = a_{\lambda,i,h,k}$ and $s_{\lambda,j,h,k} = b_{\lambda,j,h,k}$. Let $(\mathbf{r}, \mathbf{q})$ be a concrete rule, then $\mathcal{C} \big|_{(\mathbf{r}, \mathbf{q})} = \{c_{\lambda,u,\omega,h}(w_{\lambda,i,h,k}, s_{\lambda,j,h,k}) \text{ with } (\mathbf{W}, \mathbf{S}) \rightarrow (\mathbf{r}, \mathbf{q})\}$. Let N, Q be two sets of rules and $N \times Q$ their cartesian product, then $\mathcal{C} \big|_{N \times Q} = \{\mathcal{C} \big|_{(\mathbf{r}_a, \mathbf{q}_b)} \text{ with } (\mathbf{r}_a, \mathbf{q}_b) \in N \times Q\}$. It is obvious that we can apply the above evaluation procedure not only to the entire sets $\mathcal{L}, \mathcal{M}$ and $\mathcal{C}$ but to any subset of them, even to just one element. For instance, $L_{\lambda,u,h} \big|_{\mathbf{r}_1}$ denotes the evaluation of the δ -polynomial $L_{\lambda,u,h}$ over the specific substitution rule $\mathbf{r}_1$.

Example 4.1 *Let us have the $\delta\epsilon$ -polynomial:*

$$\begin{aligned} A = & \delta_0 - 2\delta_1 + 2\delta_1\delta_2 + 4\delta_2^2 + \frac{1}{2}\delta_2\delta_3 - 2\delta_2\delta_4 + \frac{1}{4}\delta_4^2 + 3\epsilon_2 + 16\epsilon_1^2 - 18\epsilon_1\epsilon_2 - 2\epsilon_1^2\epsilon_2 + \\ & + 5\epsilon_2^2 + 2\epsilon_1\epsilon_2^2 - \frac{1}{2}\epsilon_2^3 + \epsilon_1^2\epsilon_3 - \epsilon_1\epsilon_2\epsilon_3 + \frac{1}{4}\epsilon_2^2\epsilon_3 + \delta_1\delta_2\epsilon_1 + \frac{1}{4}\delta_2^2\epsilon_1 + \frac{1}{2}\delta_1\delta_3\epsilon_1 - \\ & - \frac{1}{16}\delta_3^2\epsilon_1 - 4\delta_1\delta_2\epsilon_2 + \delta_2^2\epsilon_2 + 2\delta_1\delta_3\epsilon_2 - \frac{1}{4}\delta_3^2\epsilon_2 \end{aligned} \quad (7)$$

In order to clarify the notion of Linear Factors, we shall follow the FLF-Algorithm step by step. We shall begin by working with the δ -part of A , $A_\delta = \delta_0 - 2\delta_1 + 2\delta_1\delta_2 + 4\delta_2^2 + \frac{1}{2}\delta_2\delta_3 - 2\delta_2\delta_4 + \frac{1}{4}\delta_4^2$. The linear part of A_δ is $\delta_0 - 2\delta_1$ and hence $L_{0,1,0} = \delta_0 - 2\delta_1$. This polynomial, which is not formal, is the first member of the set $\mathcal{L}$. Now, the maximum term of the nonlinear part of A_δ is $\frac{1}{4}\delta_4^2$ and the REM-Substep 3e will give: $R = A_{\delta,nl} - \frac{1}{4}\delta_0^2\epsilon_e * [L_{1,1,0}, M_{1,0,0}]$ with $L_{1,1,0} = w_{1,1,0,0}\delta_0 + w_{1,1,0,1}\delta_1 + w_{1,1,0,2}\delta_2 + w_{1,1,0,3}\delta_3 + \delta_4$, $M_{1,0,0} = \epsilon_e$, this $L_{1,1,0}$ is the next member of $\mathcal{L}$ and $\text{ccoef}(L_{1,1,0}) = -\frac{1}{4}$, $\mathcal{O} = \mathcal{O} \cup \{\delta_0^2\epsilon_e\}$. Now, the higher ordered term of the obtained polynomial R , is $-\frac{w_{1,1,0,3}}{2}\delta_3\delta_4$ and the REM-Substep 3e will give $R_{new} = R_{old} + \frac{w_{1,1,0,3}}{2}\delta_0\delta_1\epsilon_e * [L_{2,1,0}, M_{2,0,0}]$ with $L_{2,1,0} = w_{2,1,0,0}\delta_0 + w_{2,1,0,1}\delta_1 + w_{2,1,0,2}\delta_2 + \delta_3$ and $M_{2,0,0} = \epsilon_e$. Working similarly we shall finally get the next expression for A_δ :

$$A_\delta = \delta_0 - 2\delta_1 + \frac{1}{4}\delta_0^2 * (w_{1,1,0,0}\delta_0 + w_{1,1,0,1}\delta_1 + w_{1,1,0,2}\delta_2 + w_{1,1,0,3}\delta_3 + \delta_4) - \frac{w_{1,1,0,3}}{2}\delta_0\delta_1 * (w_{2,1,0,0}\delta_0 + w_{2,1,0,1}\delta_1 + w_{2,1,0,2}\delta_2 + \delta_3) - \frac{w_{1,1,0,3}w_{2,1,0,2}}{2}\delta_0\delta_1\delta_2 + \dots$$

$$\begin{aligned}
&*(w_{3,1,0,0}\delta_0 + w_{3,1,0,1}\delta_1 + \delta_2) + c_4\delta_0\delta_4*(w_{4,1,0,0}\delta_0 + \delta_1) + c_5\delta_0^2*(w_{5,1,0,0}\delta_0 + w_{5,1,0,1}\delta_1 + w_{5,1,0,2}\delta_2 + \delta_3) + \\
&+ c_6\delta_0\delta_1*(w_{6,1,0,0}\delta_0 + w_{6,1,0,1}\delta_1 + \delta_2) + c_7\delta_0\delta_2*(w_{7,1,0,0}\delta_0 + \delta_1) + c_8\delta_0^2*(w_{8,1,0,0}\delta_0 + w_{8,1,0,1}\delta_1 + \delta_2) + \\
&+ c_9\delta_0\delta_1*(w_{9,1,0,0}\delta_0 + \delta_1) + c_{10}\delta_0^2*(w_{10,1,0,0}\delta_0 + \delta_1) + R
\end{aligned}$$

where R contains only zero terms, particularly $R = r_0\delta_0^2 + r_1\delta_0\delta_1 + r_2\delta_0\delta_2 + r_3\delta_0\delta_3$. The coefficients $c_4, c_5, c_6, c_7, c_8, c_9, c_{10}, r_0, r_1, r_2, r_3$ are polynomial functions of the $w_{\lambda,u,h,i}$ parameters. They are not presented explicitly due to their large size (the coefficient c_{10} , for instance, contains 77 monomials). We factorize R by δ_0 and we get: $R = \delta_0\tilde{R} = \delta_0(r_0\delta_0 + r_1\delta_1 + r_2\delta_2 + r_3\delta_3)$ and we repeat the procedure with $A_\delta = r_0\delta_0 + r_1\delta_1 + r_2\delta_2 + r_3\delta_3$. Since it is linear the SUBROUTINE REMAINDER will terminate at REM-STEP 2, giving $L_{0,2,0} = r_0\delta_0 + r_1\delta_1 + r_2\delta_2 + r_3\delta_3$ and $c_{\text{coef}}(L_{0,2,0}) = 1$, $\mathcal{O} = \mathcal{O} \cup \{\delta_0\}$. All the above linear polynomials are elements of $\mathcal{L}$. We are now in Step 4, working with the ϵ -part of A , $A_\epsilon = 3\epsilon_2 + 16\epsilon_1^2 - 18\epsilon_1\epsilon_2 - 2\epsilon_1^2\epsilon_2 + 5\epsilon_2^2 + 2\epsilon_1\epsilon_2^2 - \frac{1}{2}\epsilon_2^3 + \epsilon_1^2\epsilon_3 - \epsilon_1\epsilon_2\epsilon_3 + \frac{1}{4}\epsilon_2^2\epsilon_3$. Initially, we get $M_{0,1,0} = 3\epsilon_2$ and for the nonlinear part of A_ϵ we shall finally get:

$$\begin{aligned}
A_{\epsilon,nl} = & \frac{1}{4}\epsilon_0^2\epsilon_1*(s_{1,1,0,0}\epsilon_0 + s_{1,1,0,1}\epsilon_1 + \epsilon_2) + \left(-1 - \frac{s_{1,1,0,1}}{2}\right)\epsilon_0\epsilon_1\epsilon_2*(s_{2,1,0,0}\epsilon_0 + \epsilon_1) + \\
& + \left(1 - \frac{s_{1,1,0,1}}{4} + s_{2,1,0,0} + \frac{s_{1,1,0,1}s_{2,1,0,0}}{2}\right)\epsilon_0^2\epsilon_2*(s_{3,1,0,0}\epsilon_0 + \epsilon_1) + \left(-\frac{1}{2} - \frac{s_{1,1,0,1}}{4}\right)\epsilon_0^3* \\
& *(s_{4,1,0,0}\epsilon_0 + s_{4,1,0,1}\epsilon_1 + \epsilon_2) + \tilde{c}_5\epsilon_0\epsilon_1^2*(s_{5,1,0,0}\epsilon_0 + \epsilon_1) + \tilde{c}_6\epsilon_0^2\epsilon_1*(s_{6,1,0,0}\epsilon_0 + \epsilon_1) + \\
& + \tilde{c}_7\epsilon_0^3*(s_{7,1,0,0}\epsilon_0 + \epsilon_1) + 5\epsilon_0^2*(s_{8,1,0,0}\epsilon_0 + s_{8,1,0,1}\epsilon_1 + \epsilon_2) + (-18 - 10s_{8,1,0,1})\epsilon_0\epsilon_1* \\
& *(s_{9,1,0,0}\epsilon_0 + \epsilon_1) + \tilde{c}_{10}\epsilon_0^2*(s_{10,1,0,0}\epsilon_0 + \epsilon_1) + R
\end{aligned}$$

The coefficients $\tilde{c}_5, \tilde{c}_6, \tilde{c}_7, \tilde{c}_{10}$ have large size and therefore are not written in details. The quantity R is $R = r_{2,3}\epsilon_0\epsilon_2\epsilon_3 + r_{1,2}\epsilon_0\epsilon_1\epsilon_2 + r_{0,3}\epsilon_0^2\epsilon_3 + r_{0,1}\epsilon_0^2\epsilon_1 + r_{2,2}\epsilon_0\epsilon_2^2 + r_{1,3}\epsilon_0\epsilon_1\epsilon_3 + r_{0,0}\epsilon_0^3 + r_{1,1}\epsilon_0\epsilon_1^2 + r_{0,2}\epsilon_0^2\epsilon_2 + r_{2,\epsilon_0}\epsilon_2 + r_{1,\epsilon_0}\epsilon_1 + r_{0,\epsilon_0}\epsilon_0^2$. Factorizing R by ϵ_0 we get $R = \epsilon_0 \cdot \tilde{R}$ and then we repeat the substeps of step 4 once more, taking $\omega = 2$, $M_{0,2,0} = r_0\epsilon_0 + r_1\epsilon_1 + r_2\epsilon_2$ and $R = r_{2,3}\epsilon_2\epsilon_3 + r_{1,2}\epsilon_1\epsilon_2 + r_{0,3}\epsilon_0\epsilon_3 + r_{0,1}\epsilon_0\epsilon_1 + r_{2,2}\epsilon_2^2 + r_{1,3}\epsilon_1\epsilon_3 + r_{0,0}\epsilon_0^2 + r_{1,1}\epsilon_1^2 + r_{0,2}\epsilon_0\epsilon_2$. The running of the substeps of REM-STEP 3 will finally give $R = \tilde{r}_{0,1}\epsilon_0\epsilon_1*(s_{1,2,0,0}\epsilon_0 + s_{1,2,0,1}\epsilon_1 + \epsilon_2) + \tilde{r}_{0,2}\epsilon_0\epsilon_2*(s_{2,2,0,0}\epsilon_0 + \epsilon_1) + \tilde{r}_{0,0}\epsilon_0^2*(s_{3,2,0,0}\epsilon_0 + s_{3,2,0,1}\epsilon_1 + \epsilon_2) + \tilde{r}_{0,1}\epsilon_0\epsilon_1*(s_{4,2,0,0}\epsilon_0 + \epsilon_1) + \tilde{r}_{0,0}\epsilon_0^2*(s_{5,2,0,0}\epsilon_0 + \epsilon_1) + R$ with $R = \hat{r}_0\epsilon_0^2 + \hat{r}_1\epsilon_0\epsilon_1 + \hat{r}_2\epsilon_0\epsilon_2 + \hat{r}_3\epsilon_0\epsilon_3$ and $\tilde{r}_{0,0}, \tilde{r}_{0,1}, \tilde{r}_{0,2}, \hat{r}_0, \hat{r}_1, \hat{r}_2, \hat{r}_3$ are polynomials of all the above parameters. Visiting SUB-Step 4b once more we shall take $R = \epsilon_0 \cdot (\hat{r}_0\epsilon_0 + \hat{r}_1\epsilon_1 + \hat{r}_2\epsilon_2 + \hat{r}_3\epsilon_3)$. Now, $\omega = 3$ and since $\tilde{R}$ is linear the SUBROUTINE REMAINDER will terminate by giving $M_{0,3,0} = \hat{r}_0\epsilon_0 + \hat{r}_1\epsilon_1 + \hat{r}_2\epsilon_2 + \hat{r}_3\epsilon_3$. All the above appeared linear polynomials are elements of $\mathcal{M}$. We go now to step 5, working with the $\delta\epsilon$ -part of A , $A_{\delta\epsilon} = \delta_1\delta_2\epsilon_1 + \frac{1}{4}\delta_2^2\epsilon_1 + \frac{1}{2}\delta_1\delta_3\epsilon_1 - \frac{1}{16}\delta_3^2\epsilon_1 - 4\delta_1\delta_2\epsilon_2 + \delta_2^2\epsilon_2 + 2\delta_1\delta_3\epsilon_2 - \frac{1}{4}\delta_3^2\epsilon_2$. We have $u = 0, \omega = 0$ and successive applications of the substeps of REM-STEP 3, will finally give the following expression for $A_{\delta\epsilon}$:

$$\begin{aligned}
A_{\delta\epsilon} = & -\frac{1}{4}\delta_0^2\epsilon_0*[w_{1,0,0,0}\delta_0 + w_{1,0,0,1}\delta_1 + w_{1,0,0,2}\delta_2 + \delta_3, s_{1,0,0,0}\epsilon_0 + s_{1,0,0,1}\epsilon_1 + \epsilon_2] + \\
& + \left(-\frac{1}{16} + \frac{s_{1,0,0,1}}{4}\right)\delta_0^2\epsilon_0*[w_{2,0,0,0}\delta_0 + w_{2,0,0,1}\delta_1 + w_{2,0,0,2}\delta_2 + \delta_3, s_{2,0,0,0}\epsilon_0 + \epsilon_1] + \\
& + (s_{1,0,0,0} - s_{2,0,0,0} - s_{1,0,0,1}s_{2,0,0,0})\epsilon_2 + \dots
\end{aligned}$$

$$\begin{aligned}
& + \frac{w_{1,0,0,2}}{2} \delta_0 \delta_1 \epsilon_0 * [w_{4,0,0,0} \delta_0 + w_{4,0,0,1} \delta_1 + \delta_2, s_{4,0,0,0} \epsilon_0 + s_{4,0,0,1} \epsilon_1 + \epsilon_2] + p_5 \delta_0 \delta_1 \epsilon_0 * [w_{5,0,0,0} \delta_0 + w_{5,0,0,1} \delta_1 + \\
& \quad + \delta_2, s_{5,0,0,0} \epsilon_0 + \epsilon_1] + p_6 \delta_0 \delta_1 \epsilon_0 * [w_{6,0,0,0} \delta_0 + w_{6,0,0,1} \delta_1 + \delta_2, \epsilon_0] + \\
& \quad + \left(2 + \frac{s_{1,0,0,1}}{2} - \frac{s_{1,0,0,2} s_{4,0,0,1}}{2} \right) \delta_0 \delta_2 \epsilon_0 * [w_{7,0,0,0} \delta_0 + \delta_1, s_{7,0,0,0} \epsilon_0 + s_{7,0,0,1} \epsilon_1 + \epsilon_2] + \\
& \quad + p_8 \delta_0 \delta_2 \epsilon_0 * [w_{8,0,0,0} \delta_0 + \delta_1, s_{8,0,0,0} \epsilon_0 + \epsilon_1] + p_9 \delta_0 \delta_2 \epsilon_0 * [w_{9,0,0,0} \delta_0 + \delta_1, \epsilon_0] + p_{10} \delta_0^2 \epsilon_0 * \\
& \quad * [w_{10,0,0,0} \delta_0 + w_{10,0,0,1} \delta_1 + \delta_2, s_{10,0,0,0} \epsilon_0 + s_{10,0,0,1} \epsilon_1 + \epsilon_2] + p_{11} \delta_0^2 \epsilon_0 * [w_{11,0,0,0} \delta_0 + w_{11,0,0,1} \delta_1 + \delta_2, \\
& \quad s_{11,0,0,0} \epsilon_0 + \epsilon_1] + p_{12} \delta_0^2 \epsilon_0 * [w_{12,0,0,0} \delta_0 + w_{12,0,0,1} \delta_1 + \delta_2, \epsilon_0] + p_{13} \delta_0 \delta_1 \epsilon_0 * [w_{13,0,0,0} \delta_0 + \delta_1, \epsilon_2] + \\
& \quad + p_{14} \delta_0 \delta_1 \epsilon_0 * [w_{14,0,0,0} \delta_0 + \delta_1, s_{14,0,0,0} \epsilon_0 + \epsilon_1] + \dots + R
\end{aligned}$$

where $R = q_0 \delta_0^2 \epsilon_0 + q_1 \delta_0 \delta_1 \epsilon_0 + q_2 \delta_0 \delta_2 \epsilon_0 + q_3 \delta_0 \delta_3 \epsilon_0$. Since $R = \delta_0 \epsilon_0 \cdot \tilde{R} = \delta_0 \epsilon_0 (q_0 \delta_0 + q_1 \delta_1 + q_2 \delta_2 + q_3 \delta_3)$ the algorithm will terminate with $L_{0,0,1} = q_0 \delta_0 + q_1 \delta_1 + q_2 \delta_2 + q_3 \delta_3$. Summarizing, the final output of the algorithm is $\mathcal{L} = \{\delta_0 - 2\delta_1, w_{1,1,0,0} \delta_0 + w_{1,1,0,1} \delta_1 + w_{1,1,0,2} \delta_2 + w_{1,1,0,3} \delta_3 + \delta_4, w_{2,1,0,0} \delta_0 + w_{2,1,0,1} \delta_1 + w_{2,1,0,2} \delta_2 + \delta_3, \dots\}$, $\mathcal{M} = \{3\epsilon_2, s_{1,1,0,0} \epsilon_0 + s_{1,1,0,1} \epsilon_1 + \epsilon_2, s_{2,1,0,0} \epsilon_0 + \epsilon_1, \dots\}$, $\mathcal{O} = \{\delta_0, \delta_4^2, \delta_0 \delta_1, \dots, \epsilon_0, \epsilon_0^2 \epsilon_1, \dots, \delta_0^2 \epsilon_0, \dots\}$, $\mathcal{C} = \{1, \frac{1}{4}, -\frac{w_{1,1,0,3}}{2}, -2 - \frac{w_{1,1,0,2}}{2} + \frac{w_{1,1,0,3} w_{2,1,0,2}}{2}, c_4, c_5, \dots, \frac{1}{4}, -1 - \frac{s_{1,1,0,1}}{2}, \dots, \tilde{c}_5, \dots, -\frac{1}{4}, -\frac{1}{16} + \frac{s_{1,0,0,1}}{4}, \dots, p_5, p_5, \dots\}$ and $R_{\epsilon, \nu} = R_{\delta, \nu} = 0$, $h^* = 1$, $R_{\delta \epsilon, 0} = R_{\delta \epsilon, 1} = 0$. Moreover, $\mathcal{L}_\delta = \mathcal{L} - \{r_0 \delta_0 + r_1 \delta_1 + r_2 \delta_2 + r_3 \delta_3\}$, $\mathcal{L}^* = \mathcal{L} - \{\delta_0 - 2\delta_1\}$, $\mathcal{M}^* = \mathcal{M} - \{3\epsilon_2\}$, $\overline{\mathcal{L}} = \mathcal{L} - \{w_{1,0,0,0} \delta_0 + w_{1,0,0,1} \delta_1 + w_{1,0,0,2} \delta_2 + \delta_3, \dots\}$, $\overline{\mathcal{M}} = \mathcal{M} - \{s_{1,0,0,0} \epsilon_0 + s_{1,0,0,1} \epsilon_1 + \epsilon_2, \dots\}$, $\overline{\mathcal{L}}^* = \overline{\mathcal{L}} - \{\delta_0 - 2\delta_1\}$, $\overline{\mathcal{M}}^* = \overline{\mathcal{M}} - \{3\epsilon_2\}$. Let us consider now the rules $\mathbf{r}_1 = \{w_{h,u,\omega,\lambda} = 1\}$, $\mathbf{r}_2 = \{w_{1,1,0,3} = 0, w_{1,1,0,2} = -4, w_{3,1,0,1} = 0, w_{4,1,0,0} = 0, w_{1,1,0,1} = 0, \text{ all the other } w\text{-parameters take arbitray values}\}$, $\mathbf{q}_1 = \{s_{h,u,\omega,\lambda} = 1\}$, $\mathbf{q}_2 = \{s_{1,0,0,1} = 0 \text{ all the other } s\text{-parameters take arbitray values}\}$, then $\mathcal{L}|_{\mathbf{r}_1} = \{\delta_0 - 2\delta_1, \delta_0 + \delta_1 + \delta_2 + \delta_3 + \delta_4, \delta_0 + \delta_1 + \delta_2 + \delta_3, \dots\}$, $\mathcal{L}_\delta|_{\mathbf{r}_2} = \{\delta_0 - 2\delta_1, w_{1,1,0,0} \delta_0 - 4\delta_2, w_{2,1,0,0} \delta_0 + w_{2,1,0,1} \delta_1 + w_{2,1,0,2} \delta_2 + \delta_3, \dots\}$, $A_\delta|_{\mathbf{r}_2} = \delta_0 - 2\delta_1 + \frac{1}{4} \delta_0^2 * (w_{1,1,0,0} \delta_0 - 4\delta_2) + \frac{1}{2} \delta_0 \delta_1 * (w_{6,1,0,0} \delta_0 + w_{6,1,0,0} \delta_1 + \delta_2) + R|_{\mathbf{r}_2}$, $\mathcal{M}|_{\mathbf{q}_1} = \{3\epsilon_2, \epsilon_0 + \epsilon_1 + \epsilon_2, \epsilon_0 + \epsilon_1, \dots\}$ and finally $c_{2,0,0,0}|_{(\mathbf{r}_2, \mathbf{q}_2)} = \left(-\frac{1}{16} + \frac{s_{1,0,0,1}}{4}\right)|_{(\mathbf{r}_2, \mathbf{q}_2)} = -\frac{1}{16}$.

5 The Model Matching Problem

In this section we present the main application of our methodology. Before we examine it, we would like to begin by a short algebraic description of the non-linear discrete input-output systems, via the notion of $\delta\epsilon$ -polynomials. Suppose that we have a system of the form (1). By using $\delta\epsilon$ -operators we can rewrite this as follows: $F[y(t), u(t)] = 0$, where F is a $\delta\epsilon$ -polynomial. As usual, many times we decompose F to its pure δ , ϵ and $\delta\epsilon$ -parts, i.e. $F = F_\delta + F_\epsilon + F_{\delta\epsilon}$ and F_δ, F_ϵ to their linear and nonlinear parts: $F_\delta = F_{\delta,l} + F_{\delta,nl}$, $F_\epsilon = F_{\epsilon,l} + F_{\epsilon,nl}$. ($F_{\delta\epsilon}$ is already purely nonlinear). The causality and solvability of the system is guaranteed by the equality $d(F) = d(F_{\delta,l})$. Often, we shift all the delays properly so that $d(F) = d(F_{\delta,l}) = 0$, which means that the lower delayed term, i.e. $y(t)$, appears in the linear δ -part of the system and thus we can solve (1) with respect to $y(t)$ in a direct way. To each nonlinear system of the form (1) we assign a vector of real numbers $\mathbf{y}_0 = (y_0, y_1, \dots, y_{k-1})$ which gives the so called initial conditions: $y(0) = y_0, y(1) = y_1, \dots, y(k-1) = y_{k-1}$, where k is the maximum delay appeared in the output signal. Since the signals, involved in (1), are causal, i.e. $y(t) = 0, u(t) = 0$, for $t < 0$, for each given

satisfies (1), for $n \geq k$. Let $K = \sum_{i=0}^{k-1} \tau_i \delta_i$ be a linear δ -polynomial, we say that the initial conditions $\mathbf{y}_0$ satisfy the relation $K\mathbf{y}_0 = 0$ if $\sum_{i=0}^{k-1} \tau_i y_{k-1-i} = 0$. Let us have two causal nonlinear systems: $F[y(t), u(t)]$ with $\mathbf{y}_0 = (y_0, y_1, \dots, y_{k-1})$ and $\hat{F}[\psi(t), v(t)]$ with $\psi_0 = (\psi_0, \psi_1, \dots, \psi_{\lambda-1})$ and $k > \lambda$. We say that the two systems "operate" under identical initial conditions, if $\psi_0 = y_0, \psi_1 = y_1, \dots, \psi_{\lambda-1} = y_{\lambda-1}$ and $y_\lambda = \psi(\lambda), y_{\lambda+1} = \psi(\lambda+1), \dots, y_{k-1} = \psi(k-1)$. In other words we must give as initial conditions to the system which starts to produce outputs later, the corresponding outputs of the other system. The next theorem is crucial for the model matching problem. Its proof can be found at [9].

Theorem 5.1 *Let $Gy(t) = 0$ and $\Phi y^*(t) = 0$, G, Φ a nonlinear and a linear δ -polynomials be two systems without inputs, a nonlinear and a linear one, (actually they are difference equations with respect to $y(t)$ and $y^*(t)$). If $G = \hat{G} * \Phi$, then $y(t) = y^*(t)$ whenever the two systems operate under identical initial conditions. If $G = \hat{G} * \Phi$ and $\Phi = \tilde{\Phi} * \Phi$, then $y(t) = y^*(t)$ whenever the two systems operate under identical initial conditions $\mathbf{y}_0$, which satisfy the relation $\tilde{\Phi}\mathbf{y}_0 = 0$.*

The model matching problem for input - output discrete systems has already attracted a lot of attention. Though there is already a clear understanding of the linear problem [17], [21], the non-linear case is still being examined and is the subject matter of a large number of papers (see for instance [11],[25],[22], to mention but a few).

In this paper we examine the Model Matching Problem (MMP) for non-linear discrete systems of the form (1), or $F[y(t), u(t)] = 0$, F a $\delta\epsilon$ -polynomial, by using the entire algebraic background that has been previously developed. This approach is a continuation of research on non-linear discrete systems in [10],[11],[14],[12], [15]. Our aim is to find a feedback relation of the form $u(t) = Sy(t)$, S a linear δ -polynomial, so that if it is fed back to the original system we get an output that is identical to that of a given desired linear system, described by the equation $A_d y^*(t) = 0$, A_d a linear δ -polynomial. If this holds, we say that the nonlinear systems matches the linear one.

To achieve a solution of the problem we work as follows: First by means of the *FLF*-Algorithm we obtain all the linear factors of the nonlinear system and then we rewrite F as in (5). By substituting the feedback relation $u(t) = Sy(t)$, we eliminate the input signal $u(t)$ and we take an expression containing only the output signal $y(t)$, actually we have a difference equation with respect to $y(t)$. The majority of the terms, appeared in this difference expression contain either the formal δ -linear factors or the formal ϵ -linear factors of F or the "free" linear polynomial S . The cornerstone of our approach is the following: if we can achieve to find values of the parameters w_{ijhk}, s_{ijhk} and of the free linear polynomial S , so that all the terms of the said difference equation (formal and no-formal), have a common factor which is a factor of A_d as well, then, these specific values of S will constitute a solution of the model matching problem. To accomplish this task we examine several cases. In all of them we eliminate the unnecessary remainders and some of the linear factors and then we "ask" from the linear parts of the original systems (which do not have parametrical coefficients and thus cannot be influenced by the choice of proper values) to have a common factor. This can be achieved by solving certain Diophantine equations. Two things are remarkable here, first we do not get a single solution but a class of solutions, parameterized via a linear polynomial Q . Proper choice of this polynomial can create a causal feedback-law or a law with as much or as few delays we like. Secondly, and most important, all the calculations and procedures are devoted to

in section 2 the star-product of linear δ or ϵ -polynomials coincides with the usual product among univariate polynomials. Hence, we can use all the available results and tools of the classical algebraic geometry or computational algebra, to carry out the manipulations we need. Before we present a symbolic algorithm, named the MM-Algorithm, which solves the problem completely, we shall describe the GCD-Values Algorithm. This algorithm will be used as a subroutine of the main algorithm. What it essentially does is to discover those values of the parameters which permit to a set of formal linear polynomials to have a common factor. To achieve that it works in two steps: firstly it discovers the values of the parameters which make certain companion coefficients no-zero and thus the corresponding linear factors are present in the expression (6) and then it selects among these values, those specific ones which allow the corresponding linear polynomials to have a common factor.

The GCD-Values-Algorithm

Input: The set a formal linear polynomials $\mathcal{F}$.

Output: The set of rules $GCDV(\mathcal{F})$.

STEP 0: We set $GCDV(\mathcal{F}) = \{\}$ and $m = \text{card}(\mathcal{F})$, that is m is the amount of polynomials contained into $\mathcal{F}$.

STEP 1: FOR $n = 1$ **TO** m

Step 1a: We construct the power set $\mathbf{P}$, consisting from all the subsets of $\mathcal{F}$, with n elements, i.e. $\mathbf{P} = \{\mathcal{A} : \mathcal{A} \subset \mathcal{F} \text{ with } \text{card}(\mathcal{A}) = n\}$.

STEP 2a: REPEAT for all $\mathcal{A} \in \mathbf{P}$.

STEP 2a-I: Construct the set $\mathcal{C}^{\mathcal{A}}$ of the companion coefficients of the elements of $\mathcal{A}$.

STEP 2a-II: We form the set of rules $NZ = \{\mathbf{r} : \mathbf{r} \text{ is defined by the substitution } (w_{ijhk}, s_{ijhk}) = (a_{ijhk}, b_{ijhk}), a_{ijhk}, b_{ijhk} \in \mathbf{R}, \text{ such that } \text{cccoef}(J) \neq 0, \text{ for } J \in \mathcal{A} \text{ and } \text{cccoef}(\Psi) = 0 \text{ for } \Psi \in \mathcal{F} - \mathcal{A}\}$.

STEP 2a-II: We form the set of rules $CF \subset NZ$ such that $\text{gcd}(J_i) \neq \delta_0, J_i \in \mathcal{A}|_{NZ}$ and we set $GCDV(\mathcal{F}) = GCDV(\mathcal{F}) \cup CF$.

END OF THE REPEAT

END OF THE FOR

Remark 5.1 1) *The calculation of the values of the parameters which ensure that $\text{gcd}(J_i) \neq \delta_0$, can be carried out by means of resultants theory [2].*

2) *Obviously, if $\text{gcd}(J_i) = \delta_0$, for J_i belonging to a specific set of polynomials $\mathcal{A}$, then for any set $\mathcal{B}$ with $\mathcal{A} \subset \mathcal{B}$, we shall have $\text{gcd}(J_i) = \delta_0, J_i \in \mathcal{B}$, too. Therefore, we can avoid to check any set which includes $\mathcal{A}$. This comment can reduce the whole amount of calculations, significantly.*

We are now ready to state the main algorithm of the paper.

The MM-Algorithm

Output: The sets $\mathbf{F}_1, \mathbf{F}_2, \mathbf{F}_3$.

STEP 1: We decompose the polynomial F into its linear and non-linear parts: $F = F_{\delta,l} + F_{\epsilon,l} + F_{nl}$ and we rename $A = F_{\delta,l}$ and $B = F_{\epsilon,l}$.

STEP 2: By means of the *FLF*-Algorithm we form the sets $\mathcal{L}, \mathcal{M}, \mathcal{L}^*, \mathcal{M}^*, \mathcal{L}_\delta, \bar{\mathcal{L}}, \bar{\mathcal{M}}, \bar{\mathcal{L}}^*, \bar{\mathcal{M}}^*$ and $R_{\delta,h} = R_{\epsilon,h}, h = 0, \dots, h^*, R_{\delta\epsilon}$.

STEP 3: By means of the *GCD-Values-Algorithm*, whenever it is needed, we form the following sets of rules:

- $LV = GCDV(\mathcal{L}_\delta)$
- $GV = GCDV(\mathcal{L} \cup \bar{\mathcal{M}}) \cup GCDV(\bar{\mathcal{L}} \cup \mathcal{M})$
- $MV = GCDV(\mathcal{L}^* \cup \bar{\mathcal{M}}^*) \cup GCDV(\bar{\mathcal{L}}^* \cup \mathcal{M}^*)$
- $DR = \{(w_{ijhk}) = (a_{ijhk}), a_{ijhk} \in \mathbf{R}, \text{ such that } R_{\delta,0} = 0\}$.
- $RV = \{(w_{ijhk}, s_{ijhk}) = (a_{ijhk}, b_{ijhk}), a_{ijhk}, b_{ijhk} \in \mathbf{R}, \text{ such that } R_{\delta,h} = R_{\epsilon,h} = 0, h = 0, \dots, h^*, R_{\delta\epsilon} = 0\}$

STEP 4: **IF** $LV \cap DR \neq \emptyset$ **THEN** put $\mathbf{F}_1 = \{\Phi : \Phi \text{ a common factor of } L_i \in \mathcal{L}_\delta|_{LV \cap DR}\}$.

STEP 5: **IF** $RV \cap GV \neq \emptyset$ **THEN** put $\mathbf{F}_2 = \{\Phi : \Phi \text{ a common factor of } L_i \in \mathcal{L}|_{RV \cap GV} \text{ and } M_i \in \bar{\mathcal{M}}|_{RV \cap GV}\} \cup \{\Phi : \Phi \text{ a common factor of } L_i \in \bar{\mathcal{L}}|_{RV \cap GV} \text{ and } M_i \in \mathcal{M}|_{RV \cap GV}\}$.

STEP 6: **IF** $RV \cap MV \neq \emptyset$ **THEN** put $\mathbf{F}_3 = \{\Phi : \Phi \text{ a common factor of } L_i \in \mathcal{L}^*|_{RV \cap MV} \text{ and } M_i \in \bar{\mathcal{M}}^*|_{RV \cap MV}\} \cup \{\Phi : \Phi = \text{ a common factor of } L_i \in \bar{\mathcal{L}}^*|_{RV \cap MV} \text{ and } M_i \in \mathcal{M}^*|_{RV \cap MV}\}$

STEP 7: Goto to the **Output**

The next theorem includes the feedback construction upon request.

Theorem 5.2 Let $F[y(t), u(t)] = 0$, F a $\delta\epsilon$ -polynomial, be a nonlinear discrete input-output system with cross-products. Let A be the linear output part of F , $-B$ its linear input (i.e. $F_{\delta,l} = A, F_{\epsilon,l} = -B$) and $Ady^*(t) = 0$, A_d a linear δ -polynomial, a linear desired system. Let $\mathbf{F}_i, i = 1, 2, 3$ be the outputs of the *MM-Algorithm*, after its application to the polynomial F . We suppose that at least one of the sets $\mathbf{F}_i, i = 1, 2, 3$ is nonvoid. Then:

a) If A_d belongs to some of the sets $\mathbf{F}_i, i = 1, 2, 3$, then the feedback law $u(t) = Sy(t)$, with

$$S = \begin{cases} Q * A_d, & \text{if } A_d \in \mathbf{F}_1 \\ Q, & \text{if } A_d \in \mathbf{F}_2 \\ Z_0 + Q * A_d, & \text{if } A_d \in \mathbf{F}_3 \end{cases}$$

where (R_0, Z_0) is a solution of the Diophantine equation $R * A_d + Z * B = A$, and Q an arbitrary linear δ -polynomial, gives a closed-loop system which produces an output $y(t)$ equal to $y^*(t)$, whenever the nominal nonlinear system and the linear desired one, "operate"

b) If A_d does not belong to any of the sets $\mathbf{F}_i, i = 1, 2, 3$ but there are subsets $\tilde{\mathbf{F}}_i \subseteq \mathbf{F}_i, i = 1, 2, 3$, not all of them void, such that $\gcd(A_d, \Phi) = \tilde{\Phi} \neq \delta_0$, for $\Phi \in \tilde{\mathbf{F}}_i, i = 1, 2, 3$, then, the feedback law $u(t) = Sy(t)$, with

$$S = \begin{cases} Q * \tilde{\Phi}, & \text{if } \Phi \in \tilde{\mathbf{F}}_1 \\ Q, & \text{if } \Phi \in \tilde{\mathbf{F}}_2 \\ Z_0 + Q * \tilde{\Phi}, & \text{if } \Phi \in \tilde{\mathbf{F}}_3 \end{cases}$$

where (R_0, Z_0) is a solution of the Diophantine equation $R * \tilde{\Phi} + Z * B = A$, and Q an arbitrary linear δ -polynomial, gives a closed-loop system which produces an output $y(t)$ equal to $y^*(t)$, whenever the nominal nonlinear system and the linear desired one, "operate" under identical initial conditions $\mathbf{y}_0$, which satisfy the relation $\tilde{\Phi}\mathbf{y}_0 = 0$.

Proof: Let $F[y(t), u(t)] = 0$ be the nominal plant, F a $\delta\epsilon$ -polynomial. We shall follow the MM-Algorithm step by step. By means of the FLF-Algorithm and theorem 4.2 we get the following expression for F .

$$F = \sum_{h=0}^{h^*} \sum_{\omega=0}^{\omega_h^*} \sum_{u=0}^{u_h^*} \sum_{\lambda=0}^{v_{u,\omega,h}} \delta_0^{\kappa_{u,h}} \epsilon_0^{\sigma_{\omega,h}} \cdot (c_{\lambda,u,\omega,h} \delta_{\mathbf{i}_{\lambda,u,\omega,h}} \epsilon_{\mathbf{j}_{\lambda,u,\omega,h}} * [L_{\lambda,u,h}, M_{\lambda,\omega,h}]) + \\ + \mathbf{R}_{\delta,h} + \mathbf{R}_{\epsilon,h} + R_{\delta\epsilon} \quad (8)$$

Using the border values, given at 4.2, and the fact that $L_{0,1,0} = F_{\delta,l} = A$, $M_{0,1,0} = F_{\epsilon,l} = -B$, we can split (8) as follows:

$$F = A + \sum_{u=1}^{u_0^*} \sum_{\lambda=1}^{v_{u,0,0}} \delta_0^{\kappa_{u,0}} \cdot c_{\lambda,u,0,0} \delta_{\mathbf{i}_{\lambda,u,0,0}} * L_{\lambda,u,0} + \mathbf{R}_{\delta,0} - B + \sum_{\omega=1}^{\omega_0^*} \sum_{\lambda=0}^{v_{0,\omega,0}} \epsilon_0^{\sigma_{\omega,0}} \cdot c_{\lambda,0,\omega,0} \epsilon_{\mathbf{j}_{\lambda,0,\omega,0}} * M_{\lambda,\omega,0} + \\ + \mathbf{R}_{\epsilon,0} + \sum_{\lambda=1}^{v_{0,0,0}} c_{\lambda,0,0,0} \delta_{\mathbf{i}_{\lambda,0,0,0}} \epsilon_{\mathbf{j}_{\lambda,0,0,0}} * [L_{\lambda,0,0}, M_{\lambda,0,0}] + \delta_0^{\kappa_{u_0^*,0}} \epsilon_0^{\sigma_{\omega_0^*,0}} \sum_{h=1}^{h^*} \left(L_{0,1,h} + \sum_{u=1}^{u_h^*} \sum_{\lambda=1}^{v_{u,0,h}} \delta_0^{\kappa_{u,h}} \right. \\ \cdot c_{\lambda,u,0,h} \delta_{\mathbf{i}_{\lambda,u,0,h}} * L_{\lambda,u,h} + \mathbf{R}_{\delta,h} + M_{0,1,h} + \sum_{\omega=1}^{\omega_h^*} \sum_{\lambda=1}^{v_{0,\omega,h}} \epsilon_0^{\sigma_{\omega,h}} \cdot c_{\lambda,0,\omega,h} \epsilon_{\mathbf{j}_{\lambda,0,\omega,h}} * M_{\lambda,\omega,h} + \mathbf{R}_{\epsilon,h} + \\ \left. + \sum_{\lambda=1}^{v_{0,0,h}} \delta_0^{\kappa_{u_h^*,h}} \epsilon_0^{\sigma_{\omega_h^*,h}} \cdot c_{\lambda,0,0,h} \delta_{\mathbf{i}_{\lambda,0,0,h}} \epsilon_{\mathbf{j}_{\lambda,0,0,h}} * [L_{\lambda,0,h}, M_{\lambda,0,h}] \right) + R_{\delta\epsilon} \quad (9)$$

The above expression (9), recovers the " output " part, the " input " part and the " cross-products " part, contained into the original polynomial F . By substituting (9) and the feedback relation $u(t) = Sy(t)$ into the original nonlinear discrete system, we turn it to the following difference equation with respect to $y(t)$:

$$Ay(t) + \sum_{u=1}^{u_0^*} \sum_{\lambda=1}^{v_{u,0,0}} \delta_0^{\kappa_{u,0}} y(t) \cdot c_{\lambda,u,0,0} \delta_{\mathbf{i}_{\lambda,u,0,0}} * L_{\lambda,u,0} y(t) + \mathbf{R}_{\delta,0} y(t) - B * Sy(t) + \sum_{\omega=1}^{\omega_0^*} \sum_{\lambda=1}^{v_{0,\omega,0}} \epsilon_0^{\sigma_{\omega,0}} * Sy(t)$$

$$\begin{aligned}
& \cdot c_{\lambda,0,\omega,0} \epsilon_{\mathbf{j}_{\lambda,0,\omega,0}} * M_{\lambda,\omega,0} * Sy(t) + \mathbf{R}_{\epsilon,0} * Sy(t) + \sum_{\lambda=1}^{v_{0,0,0}} c_{\lambda,0,0,0} \delta_{\mathbf{i}_{\lambda,0,0,0}} \epsilon_{\mathbf{j}_{\lambda,0,0,0}} * [L_{\lambda,0,0} y(t), M_{\lambda,0,0} * Sy(t)] + \\
& + \delta_0^{\kappa_{u_0^*,0}} y(t) \epsilon_0^{\sigma_{\omega_0^*,0}} * Sy(t) \sum_{h=1}^{h^*} \left(L_{0,1,h} y(t) + \sum_{u=1}^{u_h^*} \sum_{\lambda=1}^{v_{u,0,h}} \delta_0^{\kappa_{u,h}} y(t) \cdot c_{\lambda,u,0,h} \delta_{\mathbf{i}_{\lambda,u,0,h}} * L_{\lambda,u,h} y(t) + \right. \\
& + \mathbf{R}_{\delta,h} y(t) + M_{0,1,h} * Sy(t) + \sum_{\omega=1}^{\omega_h^*} \sum_{\lambda=1}^{v_{0,\omega,h}} \epsilon_0^{\sigma_{\omega,h}} * Sy(t) \cdot c_{\lambda,0,\omega,h} \epsilon_{\mathbf{j}_{\lambda,0,\omega,h}} * M_{\lambda,\omega,h} * Sy(t) + \mathbf{R}_{\epsilon,h} * Sy(t) + \\
& \left. + \sum_{\lambda=1}^{v_{0,0,h}} \delta_0^{\kappa_{u_h^*,h}} y(t) \epsilon_0^{\sigma_{\omega_h^*,h}} * Sy(t) \cdot c_{\lambda,0,0,h} \delta_{\mathbf{i}_{\lambda,0,0,h}} \epsilon_{\mathbf{j}_{\lambda,0,0,h}} * [L_{\lambda,0,h} y(t), M_{\lambda,0,h} * Sy(t)] \right) + \\
& R_{\delta\epsilon} * S[y(t), u(t)] = 0 \tag{10}
\end{aligned}$$

Where we used the fact that $A, L_{\lambda,u,h}, R_{\delta,h}$ are polynomials of δ -operators only, and thus they act exclusively on the output, whilst $B, M_{\lambda,u,h}, R_{\epsilon,h}$ are polynomials of ϵ -operators only, and thus they act exclusively on the input. By means of proposition 3.2 (c) we can easily prove that:

- (i) $\delta_{\mathbf{i}} \epsilon_{\mathbf{j}} * [Ly, M * Sy] = (\delta_{\mathbf{i}} * L) \cdot (\delta_{\mathbf{j}} * M * S)y(t)$, for any linear polynomials L, M, S (the operator ϵ_j has changed to δ_j , since we are dealing only with y sequences).
 - (ii) $\epsilon_0^\beta * Sy(t) = S^\beta y(t)$
 - (iii) $R_{\epsilon,h} * Sy(t) = \sum_{\beta_h} c_{\beta_h} \epsilon_0^{\beta_h} * Sy(t) = \sum_{\beta_h} c_{\beta_h} S^{\beta_h} y(t)$.
 - (iv) $R_{\delta\epsilon} = \sum_{(\alpha,\beta)} c_{(\alpha,\beta)} \delta_0^\alpha \epsilon_0^\beta * [y(t), Sy(t)] = \sum_{(\alpha,\beta)} c_{(\alpha,\beta)} \delta_0^\alpha S^\beta y(t) = y(t) = \sum_{(\alpha,\beta)} c_{(\alpha,\beta)} y^a(t) [Sy(t)]^b$.
- Therefore, after some manipulations, (10) becomes:

$$\begin{aligned}
& \left[(A - B * S) + \sum_{u=1}^{u_0^*} \sum_{\lambda=1}^{v_{u,0,0}} \delta_0^{\kappa_{u,0}} \cdot c_{\lambda,u,0,0} \delta_{\mathbf{i}_{\lambda,u,0,0}} * L_{\lambda,u,0} + \mathbf{R}_{\delta,0} + \sum_{\omega=1}^{\omega_0^*} \sum_{\lambda=1}^{v_{0,\omega,0}} c_{\lambda,0,\omega,0} S^{\sigma_{\omega,0}} \cdot (\delta_{\mathbf{j}_{\lambda,0,\omega,0}} * \right. \\
& * M_{\lambda,\omega,0} * S) + \sum_{\beta_0} c_{\beta_0} S^{\beta_0} + \sum_{\lambda=1}^{v_{0,0,0}} c_{\lambda,0,0,0} (\delta_{\mathbf{i}_{\lambda,0,0,0}} * L_{\lambda,0,0}) \cdot (\delta_{\mathbf{j}_{\lambda,0,0,0}} * M_{\lambda,0,0} * S) + \\
& + \delta_0^{\kappa_{u_0^*,0}} S^{\sigma_{\omega_0^*,0}} \cdot \sum_{h=1}^{h^*} \left(L_{0,1,h} + \sum_{u=1}^{u_h^*} \sum_{\lambda=1}^{v_{u,0,h}} \delta_0^{\kappa_{u,h}} \cdot c_{\lambda,u,0,h} \delta_{\mathbf{i}_{\lambda,u,0,h}} * L_{\lambda,u,h} + \mathbf{R}_{\delta,h} + \right. \\
& + M_{0,1,h} * S + \sum_{\omega=1}^{\omega_h^*} \sum_{\lambda=1}^{v_{0,\omega,h}} c_{\lambda,0,\omega,h} S^{\sigma_{\omega,h}} \cdot (\delta_{\mathbf{j}_{\lambda,0,\omega,h}} * M_{\lambda,\omega,h} * S) + \sum_{\beta_h} c_{\beta_h} S^{\beta_h} + \\
& \left. + \sum_{\lambda=1}^{v_{0,0,h}} c_{\lambda,0,0,h} \delta_0^{\kappa_{u_h^*,h}} S^{\sigma_{\omega_h^*,h}} \cdot (\delta_{\mathbf{i}_{\lambda,0,0,h}} * L_{\lambda,0,h}) \cdot (\delta_{\mathbf{j}_{\lambda,0,0,h}} * M_{\lambda,0,h} * S) \right) + \sum_{(\alpha,\beta)} c_{(\alpha,\beta)} \delta_0^\alpha S^\beta \Big] y(t) = 0
\end{aligned}$$

The left-hand side of (11) is a polynomial of δ -operators only. We denote it by F_f . So, (11) is nothing else than the closed-loop system we take from $F[y(t), u(t)] = 0$ by using the feedback-law $u(t) = Sy(t)$, in other words $F[y(t), Sy(t)] = F_f y(t) = 0$. We are now ready to state the main argument of this proof. Since the desired system $A_d y(t) = 0$ has no input, it is obvious that the closed-loop system will have the same dynamic behaviour as the desired one, only if we can find values for the parametrical coefficients and the unknown quantity S , such that the difference equations (11) and $A_d y(t) = 0$ have common solutions. To achieve this, we first need to use the equation (11). By means of theorem 5.1, we can establish that if we can find a set of values of the parameters so that Φ is a linear common factor of all the evaluated terms of (11), then any solution of the difference equation $\Phi y(t) = 0$, is also a solution of the equation (11). If we ensure that this Φ is a factor of the polynomial A_d , too, or it coincides with it, then we have the desired result. Therefore, we have to consider the following three cases, each of which corresponds to one of the three steps 4,5,6.

Case I. Let us suppose that $\mathbf{F}_1$ is non void and that $\Phi \in \mathbf{F}_1$. Step 4 of the MM-Algorithm implies that $LV \cap DV \neq \emptyset$. This condition means that we can find at least a rule of substitutions for the parameters $(w_{\lambda,u,h,k}, s_{\lambda,\omega,h,k})$, named $\mathbf{q}$, such that two targets are accomplished simultaneously: (i) The remainder $R_{\delta,0}$ is eliminated. This is due to the fact that $\mathbf{q} \in DR$. (ii) There is a certain amount of polynomials $L_{\lambda,u,0}$ with $ccoe f(L_{\lambda,u,0})|_{\mathbf{q}} \neq 0$ (thus the polynomials $L_{\lambda,u,0}|_{\mathbf{q}}$ are not anihilated from $F_f|_{\mathbf{q}}$ and hence we can calculate their great common divider) and $\gcd(L_{\lambda,u,0}|_{\mathbf{q}} \in \mathcal{L}_{\delta}|_{\mathbf{q}}) = \Phi \neq \delta_0$. This is due to the fact that $\mathbf{q} \in LV$ and the construction of the GCDV-Algorithm. Now, we set $S = Q * \Phi$, Q an arbitrary linear polynomial. Since $A \in \mathcal{L}_{\delta}|_{\mathbf{q}}$, (A has not parametrical coefficients) $\Rightarrow A = T * \Phi$, for some T and hence $A - B * S = T * \Phi - B * Q * \Phi = (T - B * Q) * \Phi = K * \Phi$ and so Φ is a factor of $A - B * S$, too. Observing that S is a factor of all the terms of (11), except the terms of the first line and taking into account all the above posed arguments and the structure of F_f , we finally conclude that Φ is a factor of all the terms of $F_f|_{\mathbf{q}}$, in other words $F_f|_{\mathbf{q}} = \hat{F}_f * \Phi$. Now, if $A_d = \Phi$ then, by means of theorem 5.1 we get that the nonlinear system matches the desired linear one under any initial conditions $\mathbf{y}_0$. If $\gcd(A_d, \Phi) = \tilde{\Phi} \neq \delta_0$ then, by means of theorem 5.1 we get that the nonlinear system matches the desired linear one under any initial conditions $\mathbf{y}_0$, which satisfy the relation $\tilde{\Phi} \mathbf{y}_0 = 0$. All the above are valid for any polynomial $\Phi \in \mathbf{F}_1$ and hence the first branch of the feedback law of theorem 5.2 has been proved.

Case II. In this, rather extreme case, we want to find a common factor Φ of the terms of (11), by leaving the polynomial S totally free. Let us suppose, as before, that $\mathbf{F}_2$ is non void and that $\Phi \in \mathbf{F}_2$. Step 5 of the MM-Algorithm implies that $RV \cap GV \neq \emptyset$. This condition ensures that there is at least one rule $\mathbf{q}$ such that all the remainders are eliminated and there is either a subset of the set $(\mathcal{L} \cup \overline{\mathcal{M}})|_{\mathbf{q}}$ or a subset of the set $(\overline{\mathcal{L}} \cup \mathcal{M})|_{\mathbf{q}}$ consisting from polynomials P , with no zero companion coefficients and with the property: either $\gcd(P \in (\mathcal{L} \cup \overline{\mathcal{M}})|_{\mathbf{q}}) = \Phi \neq \delta_0$ or $\gcd(P \in (\overline{\mathcal{L}} \cup \mathcal{M})|_{\mathbf{q}}) = \Phi \neq \delta_0$. Since $A \in \mathcal{L} \Rightarrow A = A_1 * \Phi$ and $B \in \mathcal{M} \Rightarrow B = B_1 * \Phi$, for some polynomials A_1, B_1 , so $A - B * S = (A_1 - B_1 * S) * \Phi$, which implies that Φ is a factor of $A - B * S$, too. From all the above we conclude that Φ is a common factor of all the terms of $F_f|_{\mathbf{q}}$, i.e. $F_f|_{\mathbf{q}} = \hat{F}_f * \Phi$, independently from the values of S . Therefore, if $A_d = \Phi$ then by means of 5.1 the nonlinear system and the linear desired one, will have the same dynamic behaviour for any initial conditions and any value

means of 5.1 the nonlinear system and the linear desired one will have the same dynamic behaviour for any initial conditions $\mathbf{y}_0$, which satisfy the equation $\tilde{\Phi}\mathbf{y}_0 = 0$ and any value of S , thus we set again $S = Q$, Q an arbitrary linear polynomial. All the above are valid for any polynomial $\Phi \in \mathbf{F}_2$ and hence the second branch of the feedback law of theorem 5.2 has been proved.

Case III. We are dealing now with a case similar to the second one. The essential difference is that the linear parts of F , which do not have parametrical coefficients are not involved to the calculation of the common factors. Let us suppose, as before, that $\mathbf{F}_3$ is non void and that $\Phi \in \mathbf{F}_3$. Step 6 of the MM-Algorithm implies that $RV \cap MV \neq \emptyset$. This condition ensures that there is at least one rule $\mathbf{q}$ such that all the remainders are eliminated and there is either a subset of the set $(\mathcal{L}^* \cup \overline{\mathcal{M}}^*)|_{\mathbf{q}}$ or a subset of the set $(\overline{\mathcal{L}}^* \cup \mathcal{M}^*)|_{\mathbf{q}}$, consisting from polynomials P , with no zero companion coefficients and with the property: either $\gcd(P \in (\mathcal{L}^* \cup \overline{\mathcal{M}}^*)|_{\mathbf{q}}) = \Phi \neq \delta_0$ or $\gcd(P \in (\overline{\mathcal{L}}^* \cup \mathcal{M}^*)|_{\mathbf{q}}) = \Phi \neq \delta_0$. These relations mean that Φ is a common factor of all the terms of $F_f|_{\mathbf{q}}$, but the term $A - B * S$. We have to choose now S properly so that this latter term is a multiplier of Φ , too. This means that $A - B * S = R * \Phi$, for some polynomial R and thus $B * S + R * \Phi = A$. This is the well-known Diophantine equation among linear polynomials, which has a solution if $\gcd(B, \Phi) | A$. If $\gcd(B, \Phi) = \delta_0$ the above assumption is true. If $\gcd(B, \Phi) = \hat{\Phi} \neq \delta_0$, then we conclude that $\gcd(A, B, \Phi) \neq \delta_0$ but this implies that $\gcd(P \in (\mathcal{L} \cup \overline{\mathcal{M}})|_{\mathbf{q}}) = \Phi \neq \delta_0$ or $\gcd(P \in (\overline{\mathcal{L}} \cup \mathcal{M})|_{\mathbf{q}}) = \Phi \neq \delta_0$ which leads us back to case II. Now, it is known that if S_0 is an initial solution of the Diophantine equation, S must have the general type: $S = S_0 + Q * \Phi$, Q an arbitrary linear polynomial. These values of S ensure that Φ is a common factor of $F_f|_{\mathbf{q}}$ and working as in the previous cases we can prove the last branch of the feedback-law design. In all of the above, causality is accomplished via a proper choice of the polynomial Q .

Example 5.1 *Let us suppose that we have the nonlinear system:*

$$\begin{aligned}
F = & y(t) - 2y(t-1) + 2y(t-1)y(t-2) + 4y(t-2)^2 + \frac{1}{2}y(t-2)y(t-3) - 2y(t-2)y(t-4) + \\
& + \frac{1}{4}y(t-4)^2 + 3u(t-2) + 16u(t-1)^2 - 18u(t-1)u(t-2) - 2u(t-1)^2u(t-2) + \\
& + 5u(t-2)^2 + 2u(t-1)u(t-2)^2 - \frac{1}{2}u(t-2)^3 + u(t-1)^2u(t-3) - u(t-1)u(t-2)u(t-3) + \\
& + \frac{1}{4}u(t-2)^2u(t-3) + y(t-1)y(t-2)u(t-1) + \frac{1}{4}y(t-2)^2u(t-1) + \frac{1}{2}y(t-1)y(t-3)u(t-1) - \\
& - \frac{1}{16}y(t-3)^2u(t-1) - 4y(t-1)y(t-2)u(t-2) + y(t-2)^2u(t-2) + \\
& + 2y(t-1)y(t-3)u(t-2) - \frac{1}{4}y(t-3)^2u(t-2)
\end{aligned}$$

or using $\delta\epsilon$ -polynomials $F[y(t), u(t)] = 0$, where F is the $\delta\epsilon$ -polynomial A , appeared in the example 4.1. We want to find a feedback law $u(t) = Sy(t)$ and some classes of desired systems A_d , which are matched by the the closed-loop system. To illustrate our approach we shall follow the MM-Algorithm in details. We shall follow the MM-Algorithm. In order to construct the sets $\mathbf{F}_1, \mathbf{F}_2, \mathbf{F}_3$ we have first to calculate the sets of rules LV, GV, MV, DR, RV .

means that any value of the parameters $(w_{\lambda,u,h,k}, s_{\lambda,\omega,h,k})$ satisfies the condition $R_{\delta_0} = 0$. We use now the GCD-Values Algorithm to discover common factors of the members of $\mathcal{L}_\delta$. Let us further suppose that we are in step 1 of this algorithm and that $n = 1$, this suggests that we shall work with only one polynomial and all the others will be "eliminated" by putting their companion coefficients equal to zero. Since $\text{ccoef}(L_{1,1,0}) = \frac{1}{4}$ and $\text{ccoef}(A) = 1$, $A = \delta_0 - 2\delta_1$, this cannot be happened. Let us now suppose that $n = 2$ and we have again to work only with the polynomials $L_{1,1,0}$ and A by eliminating the companion coefficients of all the others. A first glance at the coefficients indicates that the substitution $w_{1,1,0,3} = 0$, $w_{1,1,0,2} = -4$, $w_{1,1,0,1} = 0$, eliminates most of them, but finally the polynomial $L_{6,1,0}$ will remain to the "game" with $\text{ccoef}(L_{6,1,0}) = \frac{1}{2}$ and thus we have to go the $n = 3$ case. Here, we have a result. We obtain three polynomials with nonzero companion coefficients by means of the following rule of substitution: $NZ = \{w_{1,1,0,3} = 0, w_{1,1,0,2} = -4, w_{1,1,0,1} = 0, w_{6,1,0,1} = 0, w_{6,1,0,0} = 4\}$. These polynomials are $\mathcal{A} = \{A, L_{1,1,0}, L_{6,1,0}\}$. Now, we want to find a subset of NZ such that the polynomials $\mathcal{A}|_{NZ} = \{\delta_0 - 2\delta_1, -4\delta_2 + \delta_4 + w_{1,1,0,0}\delta_0, 4\delta_0 + \delta_2\}$ have a common factor, but since $\text{gcd}(\delta_0 - 2\delta_1, 4\delta_0 + \delta_2) = \delta_0$ this cannot be done and thus $CF = \emptyset$. Working similarly, we explore all the different cases for various values of n and we finally conclude that always $CF = \emptyset$ and so $GV = \emptyset$, which implies that $\mathbf{F}_1 = \emptyset$. Let us now investigate the case $\mathbf{F}_2$. In order to get $\mathbf{F}_2 \neq \emptyset$ all the linear polynomials, including A and B , must have common factors, but since $\text{gcd}(A, B) = \delta_0$ this is impossible and hence $\mathbf{F}_2 = \emptyset$, too. It remains only the third case. This situation is similar with the previous one but without involving the no formal polynomials A and B . This will provide us with some degrees of freedom. Indeed, the application of the GCD-Values Algorithm will supply us with the following common factor for the polynomials of the sets $\mathcal{L}^*$ and $\overline{\mathcal{M}}^*$: $\Phi = -2\delta_0 + \delta_1$. Since $R_{\epsilon,h} = 0, R_{\delta,h^*} = 0$ we finally get that $\Phi \in \mathbf{F}_3 \neq \emptyset$. It remains to specify the desired systems A_d , which can be matched by the feedback-laws given in theorem 5.2. If $A_d = \Phi$, then we seek for polynomials S and R such that

$$\delta_0 - 2\delta_1 = R * (-2\delta_0 + \delta_1) + 3\delta_2 * S$$

Solving this Diophantine equation we get a first solution $R_0 = -\frac{1}{2}\delta_0 + \frac{3}{4}\delta_1$ and $S_0 = -\frac{1}{4}\delta_0$. Therefore, the feedback-law upon request is $u(t) = Sy(t)$, with $S = -2\delta_0 + \delta_1 + Q * (-\frac{1}{4}\delta_0)$, Q arbitrary linear polynomial. This law matches the closed-loop system with A_d , for any set of initial conditions. If A_d has a common factor with Φ , then A_d must be a multiplier of Φ , since Φ is a prime linear polynomial we conclude that $A_d = t * \Phi$, T a linear polynomial. In this case, the feedback-law $u(t) = Sy(t)$, S as before, creates a closed-loop system which matches the desired system for any set of initial conditions (y_0, y_1) , which satisfy the relation $-2y_1 + y_0 = 0$, (theorem 5.2). Finally, we choose Q properly so that causality to be satisfied. For instance, by taking $Q = -8\delta_0 + 2\delta_2$, we get $S = \delta_1 - \frac{1}{2}\delta_2$ or

$$u(t) = y(t-1) - \frac{1}{2}y(t-2)$$

Example 5.2 Let us consider a very simplified model for velocity control of an aircraft, [13],

$$\dot{x}_1 = x_2 - f(x_1), \quad \dot{x}_2 = -x_2 + u, \quad y = x_1$$

where x_1 is the velocity, x_2 is the engine thrust and $f(x_1) = x_1^2 - 2x_1$ is the aerodynamic

continuous form:

$$\ddot{y} + (2y - 1)\dot{y} + y^2 - 2y = u$$

To discretize the above system we choose to use the Euler forward difference approximations, i.e. $\dot{y} = \frac{y(t+1)-y(t)}{h}$, $\ddot{y} = \frac{1}{h^2}[y(t) - 2y(t+1) + y(t+2)]$ and $h = 1$. A straight substitution and a proper shifting of the time delays, will give:

$$-\frac{1}{3}y(t) + y(t-1) - \frac{2}{3}y(t-1)y(t-2) + \frac{1}{3}y^2(t-2) = -\frac{1}{3}u(t-2) \quad (12)$$

or using δ and ϵ -polynomials, $F[y(t), u(t)] = 0$ with $F = \frac{1}{3}\delta_0 + \delta_1 - \frac{2}{3}\delta_1\delta_2 + \frac{1}{3}\delta_2^2 + \frac{1}{3}\epsilon_2$. We want to design a feedback law so that the closed-loop nonlinear system will match the stable linear system: $6y(t) = y(t-1) + y(t-2)$ or $(-6\delta_0 + \delta_1 + \delta_2)y(t) = 0$. We shall follow the MM-algorithm. The absence of nonlinear ϵ -terms, as well as of $\delta\epsilon$ -terms, simplifies the complexity of the operations. Step 2 will give the set: $\mathcal{L} = \{w_{10}\delta_0 + w_{11}\delta_1 + \delta_2, w_{20}\delta_0 + \delta_1, w_{30}\delta_0 + \delta_1, \frac{1}{3}((-w_{10}^2 + w_{11}^2w_{30}^2 - 2w_{20}w_{30}^2 - 2w_{11}w_{20}w_{30}^2)\delta_0 + (-2w_{10}w_{11} + 2w_{20}^2 + 2w_{11}w_{20}^2 + 2w_{11}^2w_{30} - 4w_{20}w_{30} - 4w_{11}w_{20}w_{30})\delta_1 + (-2w_{10} + 2w_{11}w_{20} + 2w_{20})\delta_2)\}$. At step 3 we form the following sets: $LV = \emptyset$, $GV = MV = \{w_{10} = -2x, w_{11} = x - 2, w_{20} = -2, w_{30} = -2, x \in \mathbf{R}\}$, (we did not include all the operations in details for the sake of presentation) and we find a common factor $\Phi = -2\delta_0 + \delta_1$. Since $\gcd(A_d, \Phi) = \Phi \neq \delta_0$, theorem 5.2 will give $S = S_0 + Q * \Phi$, where Q arbitrary, and S_0 satisfies the equation $R * \Phi + S * B = A$ or $R * (-2\delta_0 + \delta_1) + S * (-\frac{1}{3}\delta_2) = -\frac{1}{3}\delta_0 + \delta_1$. The latter equation will give $S = -\frac{5}{4}\delta_0$ and thus $S = -\frac{5}{4}\delta_0 + Q * (-2\delta_0 + \delta_1)$. In order to obtain a causal feedback connection we select $Q = -\frac{5}{8}\delta_0 + \delta_1$ and finally $S = -\frac{37}{8}\delta_1 + 2\delta_2$. Hence, a feedback-law upon request is $u(t) = -\frac{37}{8}y(t-1) + 2y(t-2)$. This will law will produce a close-loop system wich matches A_d for any set of initial conditions (y_0, y_1) which satisfy the relation $-2y_1 + y_0$. Please note that since the desired system is stable we have actually stabilized the nonlinear system, by using a feedback which is stable as well.

6 Concluding Remark

The aim of this paper was to describe an algebraic computational method for the study of a general class of non-linear discrete input - output systems that contain products between input and output signals. The model matching problem of these systems is solved through certain symbolic algorithms. The entire approach is based on a proper framework that involves the so-called $\delta\epsilon$ -operators and the star-product operation. We hope to be able to present current work on further applications of this method to other questions in a future paper.

References

- [1] G.Goodwin-Kwai Sang Sin: "Adaptive Filtering Prediction and Control" , Prentice Hall, 1984.
- [2] D. Cox, J. Little, D. O'Shea. "Ideals, Varieties and Algorithms" , Springer-Verlag, New York. (1997).

- [3] M. Fliess @ S.T.Glad, " An Algebraic Approach to Linear and Non-linear Control ", *Linköping University, Sweden, Report Lith-ISK-R-1573, 1994.*
- [4] M. Fliess, " Reversible linear and nonlinear discrete-time dynamics ", *IEEE Transactions on Automatic Control*, 37, (8), 1144-1153, 1992.
- [5] S.T. Glad, " Differential Algebraic Modeling of Non-Linear Systems ", *In proceedings of MTNS-89, Amsterdam, 97-105, 1989.*
- [6] Monaco S., Normand-Cyrot D., " On nonlinear digital control. " *Nonlinear Systems, Vol. 3, 127 – 155, Chapman & Hall, London, 1997.*
- [7] Conte G., Moog C.H., Perdon A.M., " *Nonlinear Control Systems. An algebraic setting* ", Springer - Verlag, London, 1999.
- [8] Califano C., Monaco S., Normand-Cyrot D., " On the problem of feedback linearization " *Systems Control Lett.* 36, Iss 1, pp 61 – 67, 1999.
- [9] S. Kotsios, " On Detecting Solutions of Polynomials Non-linear Difference Equations ". *Journal of Difference Equations and Applications*, Vol. 8 (6), pp 551-571, 2002.
- [10] S.Kotsios - N.Kalouptsidis: "BIBO Stability Criteria for a Certain Class of Non-linear Systems ". *Int. J. Control*, VOL.58, NO. 3, 707-730, 1993.
- [11] St.Kotsios and N.Kalouptsidis, "The model matching problem for a certain class of non-linear systems".*Int.J.Control*, Vol.57, NO. 4,881- 919, 1993.
- [12] St.Kotsios, "An application of Ritt's remainder algorithm to discrete polynomial control systems. " *IMA Journal of Mathematical Control and Information*, 18, 19-29, 2001.
- [13] Neil Munro, " *Symbolic Methods in Control Systems and Design*", IEE control Engineering Series 56, 1999.
- [14] S. Kotsios, "A New Factorization of Special Non-linear Discrete Systems and Its Applications", *IEEE, Transactions on Automatic Control*, Vol 45, Number 1, pp 24-33, 2000.
- [15] S.Kotsios, " A Model Matching Algorithm for a Class of Nonlinear Discrete Systems. A Symbolic Approach. " *44th IEEE Conference on Decision and Control and European Control Conference-05, Seville, Spain, 2005.*
- [16] N.Kalouptsidis, " *Signal Processing Systems, Theory and Design*", John Wiley and Sons, 1997.
- [17] T.Glad, L.Ljung, "Control Theory", Taylor and Francis, 2000.
- [18] St.Kotsios and D.Lappas. "A description of 2-Dimensional discrete polynomial dynamics." *IMA Journal of Mathematical Control and Information*, 13, 409-428, 1996.
- [19] U. Kotta, A. Zinober, P. Liu, " Transfer equivalence and realization of nonlinear higher

- [20] Rugh J. W., "*Non-linear system theory*", The John Hopkins University Press, Baltimore, 1981.
- [21] K.J.Astrom-B.Wittenmark, "*Computer Controlled Systems*", Prentice Hall, 1984.
- [22] S.T.Glad, " Nonlinear Regulators and Ritt's Remainder Algorithm", *In Colloque International Sur L'Analyse des Systemes Dynamiques Controlés*, 1990.
- [23] Sontag D.E. (1979). "Polynomial Response Maps". *Lecture Notes in Control and Information Sciences*, Springer-Verlag.
- [24] E.D.Sontag (1977): "Realization theory of discrete-time non-linear systems:Part I - the bounded case". *IEEE Transactions of Circuits and Systems*,10:342-356.
- [25] Yamanaka O., Ohmori H., Sano A, " Design Method of Exact Model-Matching Control for Finite Volterra Series Systems", *International Journal of Control*, Vol. 68, Iss 1, pp 107-124, 1997.
- [26] Pro-Chiang Yeh and Petar V. Kokotovic, "Adaptive Output-Feedback Design for a class of Nonlinear Discrete-Time Systems", *IEEE Trans. on Aut. Control*, Vol. 40, No. 9, pp 1663-1668, 1995.
- [27] Wu Wen-Tsun. " On algebricodifferential equation solving," [www.mmrc.iss.ac.cn / pub / mm22.pdf / 2.pdf](http://www.mmrc.iss.ac.cn/pub/mm22.pdf/2.pdf), Dec. 2003.